



Multi-Access Gateway – controller

Release 26.3

Log Events Reference Guide

3HE 22202 AAAA TQZZA

Edition: 01

March 2026

Nokia is committed to diversity and inclusion. We are continuously reviewing our customer documentation and consulting with standards bodies to ensure that terminology is inclusive and aligned with the industry. Our future customer documentation will be updated accordingly.

This document includes Nokia proprietary and confidential information, which may not be distributed or disclosed to any third parties without the prior written consent of Nokia.

This document is intended for use by Nokia's customers ("You"/"Your") in connection with a product purchased or licensed from any company within Nokia Group of Companies. Use this document as agreed. You agree to notify Nokia of any errors you may find in this document; however, should you elect to use this document for any purpose(s) for which it is not intended, You understand and warrant that any determinations You may make or actions You may take will be based upon Your independent judgment and analysis of the content of this document.

Nokia reserves the right to make changes to this document without notice. At all times, the controlling version is the one available on Nokia's site.

No part of this document may be modified.

NO WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY WARRANTY OF AVAILABILITY, ACCURACY, RELIABILITY, TITLE, NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE, IS MADE IN RELATION TO THE CONTENT OF THIS DOCUMENT. IN NO EVENT WILL NOKIA BE LIABLE FOR ANY DAMAGES, INCLUDING BUT NOT LIMITED TO SPECIAL, DIRECT, INDIRECT, INCIDENTAL OR CONSEQUENTIAL OR ANY LOSSES, SUCH AS BUT NOT LIMITED TO LOSS OF PROFIT, REVENUE, BUSINESS INTERRUPTION, BUSINESS OPPORTUNITY OR DATA THAT MAY ARISE FROM THE USE OF THIS DOCUMENT OR THE INFORMATION IN IT, EVEN IN THE CASE OF ERRORS IN OR OMISSIONS FROM THIS DOCUMENT OR ITS CONTENT.

Copyright and trademark: Nokia is a registered trademark of Nokia Corporation. Other product names mentioned in this document may be trademarks of their respective owners.

© 2026 Nokia.

Table of contents

| | |
|---|-----------|
| List of tables..... | 6 |
| 1 Getting started..... | 10 |
| 1.1 About this guide..... | 10 |
| 1.2 Conventions..... | 10 |
| 1.2.1 Precautionary and information messages..... | 10 |
| 1.2.2 Options or substeps in procedures and sequential workflows..... | 11 |
| 2 Log events overview..... | 12 |
| 2.1 Viewing log events..... | 13 |
| 2.2 Log event configuration..... | 15 |
| 2.2.1 Configuring SNMP as the log destination..... | 15 |
| 2.2.2 Configuring an SNMP trap destination..... | 17 |
| 2.2.3 Configuring a file as the log destination..... | 19 |
| 2.2.4 Configuring a syslog as the log destination..... | 20 |
| 2.2.5 Debugging an application..... | 21 |
| 2.3 Sample log event..... | 22 |
| 3 Log events..... | 25 |
| 3.1 MC_REDUNDANCY..... | 25 |
| 3.1.1 tmnxMcMobileBothLockedToMaster..... | 25 |
| 3.1.2 tmnxMcMobileGeoRedChgInfo..... | 26 |
| 3.1.3 tmnxMcMonitorMclcrAlarm..... | 26 |
| 3.2 MOBILE_CUPS_BNG..... | 27 |
| 3.2.1 tmnxMobBngStaticSeOperStateUp..... | 27 |
| 3.2.2 tmnxMobGwBngLockoutLimitExceeded..... | 28 |
| 3.2.3 tmnxMobGwBngNatPrefixRevocation..... | 28 |
| 3.2.4 tmnxMobGwBngResFsgUpfChange..... | 29 |
| 3.2.5 tmnxMobGwBngResFsgUpfError..... | 30 |
| 3.2.6 tmnxMobGwBngSessCreateUpfNonResp..... | 30 |
| 3.2.7 tmnxMobGwBngSessDuplAttr..... | 31 |
| 3.2.8 tmnxMobGwBngSessTermBySystem..... | 32 |
| 3.2.9 tmnxMobGwBngSubscriberCreate..... | 33 |

| | | |
|--------|---------------------------------------|----|
| 3.2.10 | tmnxMobGwBngSubscriberDelete..... | 33 |
| 3.3 | MOBILE_GATEWAY..... | 34 |
| 3.3.1 | tmnxMcRedundancyTrafficReceived..... | 34 |
| 3.3.2 | tmnxMobDbRedRoleActive..... | 34 |
| 3.3.3 | tmnxMobDbStatusChanged..... | 35 |
| 3.3.4 | tmnxMobGwApnMaxAttachLmtAlrm..... | 36 |
| 3.3.5 | tmnxMobGwApnMaxAttachLmtAlrmClr..... | 36 |
| 3.3.6 | tmnxMobGwAssociationPeerState..... | 37 |
| 3.3.7 | tmnxMobGwAssocNodeIdFail..... | 38 |
| 3.3.8 | tmnxMobGwAssocNodeIdFailClr..... | 38 |
| 3.3.9 | tmnxMobGwAssocNodeIdMismatch..... | 39 |
| 3.3.10 | tmnxMobGwAssocNodeIdMismatchClr..... | 39 |
| 3.3.11 | tmnxMobGwAssocPfcPndIdIpTypErClr..... | 40 |
| 3.3.12 | tmnxMobGwAssocPfcPndIdIpTypErr..... | 41 |
| 3.3.13 | tmnxMobGwBngChfFailAlmClr..... | 41 |
| 3.3.14 | tmnxMobGwBngChfFailAlmSet..... | 42 |
| 3.3.15 | tmnxMobGwBngPcfFailAlmClr..... | 43 |
| 3.3.16 | tmnxMobGwBngPcfFailAlmSet..... | 43 |
| 3.3.17 | tmnxMobGwBngUdmSdmFailAlmClr..... | 44 |
| 3.3.18 | tmnxMobGwBngUdmSdmFailAlmSet..... | 45 |
| 3.3.19 | tmnxMobGwBngUdmUecmFailAlmClr..... | 45 |
| 3.3.20 | tmnxMobGwBngUdmUecmFailAlmSet..... | 46 |
| 3.3.21 | tmnxMobGwCfCapacityAlarmMinor..... | 47 |
| 3.3.22 | tmnxMobGwCfCapacityAlmMjrClear..... | 47 |
| 3.3.23 | tmnxMobGwCfCapacityAlmMnrClear..... | 48 |
| 3.3.24 | tmnxMobGwCntrlFabricPartialFail..... | 48 |
| 3.3.25 | tmnxMobGwControlFabricFailure..... | 49 |
| 3.3.26 | tmnxMobGwDdnThrottlingStart..... | 50 |
| 3.3.27 | tmnxMobGwDdnThrottlingStop..... | 50 |
| 3.3.28 | tmnxMobGwDnsSnpFqdnIpLimitAlarm..... | 51 |
| 3.3.29 | tmnxMobGwLciOverload..... | 52 |
| 3.3.30 | tmnxMobGwLciOverloadClear..... | 52 |
| 3.3.31 | tmnxMobGwMcRedPurgeRebootStandby..... | 53 |
| 3.3.32 | tmnxMobGwNnrBlocklistAlarm..... | 53 |
| 3.3.33 | tmnxMobGwNnrBlocklistAlarmClear..... | 54 |
| 3.3.34 | tmnxMobGwNrfHeartbeatAlarm..... | 55 |

| | | |
|--------|--|----|
| 3.3.35 | tmnxMobGwNrfHeartbeatAlarmClear..... | 55 |
| 3.3.36 | tmnxMobGwOciOverload..... | 56 |
| 3.3.37 | tmnxMobGwOciOverloadClear..... | 56 |
| 3.3.38 | tmnxMobGwOciOvldThrtStart..... | 57 |
| 3.3.39 | tmnxMobGwOciOvldThrtStop..... | 58 |
| 3.3.40 | tmnxMobGwPathMgmtPeerState..... | 58 |
| 3.3.41 | tmnxMobGwPcmdOperStateChange..... | 59 |
| 3.3.42 | tmnxMobGwPfcRestoreInProg..... | 60 |
| 3.3.43 | tmnxMobGwPfcViaUpFuncFailureClr..... | 61 |
| 3.3.44 | tmnxMobGwRadGrpFailAlarm..... | 61 |
| 3.3.45 | tmnxMobGwRadGrpFailAlarmClrd..... | 62 |
| 3.3.46 | tmnxMobGwRadPeerFailAlarm..... | 62 |
| 3.3.47 | tmnxMobGwRadPeerFailAlarmClrd..... | 63 |
| 3.3.48 | tmnxMobGwSbiPeerState..... | 64 |
| 3.3.49 | tmnxMobPdnApnMaxPdnConnAlarm..... | 64 |
| 3.3.50 | tmnxMobPdnApnMaxPdnConnAlarmClr..... | 65 |
| 3.3.51 | tmnxMobPdnBearerContextClear..... | 66 |
| 3.3.52 | tmnxMobPdnLaaPfxInsufficientMem..... | 66 |
| 3.3.53 | tmnxMobPdnLaaPINoFreeMnets..... | 67 |
| 3.3.54 | tmnxMobPdnLaaPINumFreeMnetsLow..... | 68 |
| 3.3.55 | tmnxMobProfNodeSelTrgtSugstRebal..... | 68 |
| 3.3.56 | tmnxMobProfNodeSelTrgtSugstRevert..... | 69 |
| 3.3.57 | tmnxOverlayFabricFailure..... | 70 |
| 3.3.58 | tmnxOverlayFabricPartialFailure..... | 70 |
| 3.3.59 | tmnxOverlayFabricStatus..... | 71 |

List of tables

| | |
|--|----|
| Table 1: Log entry field descriptions..... | 12 |
| Table 2: Log event sources..... | 13 |
| Table 3: tmnxMobGwBngLockoutLimitExceeded properties..... | 23 |
| Table 4: Log entry field descriptions..... | 23 |
| Table 5: tmnxMcMobileBothLockedToMaster properties..... | 25 |
| Table 6: tmnxMcMobileGeoRedChgInfo properties..... | 26 |
| Table 7: tmnxMcMonitorMclcrAlarm properties..... | 26 |
| Table 8: tmnxMobBngStaticSeOperStateUp properties..... | 27 |
| Table 9: tmnxMobGwBngLockoutLimitExceeded properties..... | 28 |
| Table 10: tmnxMobGwBngNatPrefixRevocation properties..... | 28 |
| Table 11: tmnxMobGwBngResFsgUpfChange properties..... | 29 |
| Table 12: tmnxMobGwBngResFsgUpfError properties..... | 30 |
| Table 13: tmnxMobGwBngSessCreateUpfNonResp properties..... | 30 |
| Table 14: tmnxMobGwBngSessDuplAttr properties..... | 31 |
| Table 15: tmnxMobGwBngSessTermBySystem properties..... | 32 |
| Table 16: tmnxMobGwBngSubscriberCreate properties..... | 33 |
| Table 17: tmnxMobGwBngSubscriberDelete properties..... | 33 |
| Table 18: tmnxMcRedundancyTrafficReceived properties..... | 34 |
| Table 19: tmnxMobDbRedRoleActive properties..... | 34 |
| Table 20: tmnxMobDbStatusChanged properties..... | 35 |
| Table 21: tmnxMobGwApnMaxAttachLmtAlrm properties..... | 36 |

| | |
|--|----|
| Table 22: tmnxMobGwApnMaxAttachLmtAlmClr properties..... | 36 |
| Table 23: tmnxMobGwAssociationPeerState properties..... | 37 |
| Table 24: tmnxMobGwAssocNodeIdFail properties..... | 38 |
| Table 25: tmnxMobGwAssocNodeIdFailClr properties..... | 38 |
| Table 26: tmnxMobGwAssocNodeIdMismatch properties..... | 39 |
| Table 27: tmnxMobGwAssocNodeIdMismatchClr properties..... | 39 |
| Table 28: tmnxMobGwAssocPfcPndIdIpTypErClr properties..... | 40 |
| Table 29: tmnxMobGwAssocPfcPndIdIpTypErr properties..... | 41 |
| Table 30: tmnxMobGwBngChfFailAlmClr properties..... | 41 |
| Table 31: tmnxMobGwBngChfFailAlmSet properties..... | 42 |
| Table 32: tmnxMobGwBngPcfFailAlmClr properties..... | 43 |
| Table 33: tmnxMobGwBngPcfFailAlmSet properties..... | 43 |
| Table 34: tmnxMobGwBngUdmSdmFailAlmClr properties..... | 44 |
| Table 35: tmnxMobGwBngUdmSdmFailAlmSet properties..... | 45 |
| Table 36: tmnxMobGwBngUdmUecmFailAlmClr properties..... | 45 |
| Table 37: tmnxMobGwBngUdmUecmFailAlmSet properties..... | 46 |
| Table 38: tmnxMobGwCfCapacityAlarmMinor properties..... | 47 |
| Table 39: tmnxMobGwCfCapacityAlmMjrClear properties..... | 47 |
| Table 40: tmnxMobGwCfCapacityAlmMnrClear properties..... | 48 |
| Table 41: tmnxMobGwCntrlFabricPartialFail properties..... | 48 |
| Table 42: tmnxMobGwControlFabricFailure properties..... | 49 |
| Table 43: tmnxMobGwDdnThrottlingStart properties..... | 50 |
| Table 44: tmnxMobGwDdnThrottlingStop properties..... | 50 |

| | |
|--|----|
| Table 45: tmnxMobGwDnsSnpFqdnIpLimitAlarm properties..... | 51 |
| Table 46: tmnxMobGwLciOverload properties..... | 52 |
| Table 47: tmnxMobGwLciOverloadClear properties..... | 52 |
| Table 48: tmnxMobGwMcRedPurgeRebootStandby properties..... | 53 |
| Table 49: tmnxMobGwNnrfBlocklistAlarm properties..... | 53 |
| Table 50: tmnxMobGwNnrfBlocklistAlarmClear properties..... | 54 |
| Table 51: tmnxMobGwNrfHeartbeatAlarm properties..... | 55 |
| Table 52: tmnxMobGwNrfHeartbeatAlarmClear properties..... | 55 |
| Table 53: tmnxMobGwOciOverload properties..... | 56 |
| Table 54: tmnxMobGwOciOverloadClear properties..... | 56 |
| Table 55: tmnxMobGwOciOvldThrtStart properties..... | 57 |
| Table 56: tmnxMobGwOciOvldThrtStop properties..... | 58 |
| Table 57: tmnxMobGwPathMgmtPeerState properties..... | 58 |
| Table 58: tmnxMobGwPcmdOperStateChange properties..... | 59 |
| Table 59: tmnxMobGwPfcPRestoreInProg properties..... | 60 |
| Table 60: tmnxMobGwPfcPViaUpFuncFailureClr properties..... | 61 |
| Table 61: tmnxMobGwRadGrpFailAlarm properties..... | 61 |
| Table 62: tmnxMobGwRadGrpFailAlarmClrd properties..... | 62 |
| Table 63: tmnxMobGwRadPeerFailAlarm properties..... | 62 |
| Table 64: tmnxMobGwRadPeerFailAlarmClrd properties..... | 63 |
| Table 65: tmnxMobGwSbiPeerState properties..... | 64 |
| Table 66: tmnxMobPdnApnMaxPdnConnAlarm properties..... | 64 |
| Table 67: tmnxMobPdnApnMaxPdnConnAlarmClr properties..... | 65 |

| | |
|--|----|
| Table 68: tmnxMobPdnBearerContextClear properties..... | 66 |
| Table 69: tmnxMobPdnLaaPfxInsufficientMem properties..... | 66 |
| Table 70: tmnxMobPdnLaaPINoFreeMnets properties..... | 67 |
| Table 71: tmnxMobPdnLaaPINumFreeMnetsLow properties..... | 68 |
| Table 72: tmnxMobProfNodeSelTrgtSugstRebal properties..... | 68 |
| Table 73: tmnxMobProfNodeSelTrgtSugstRevrt properties..... | 69 |
| Table 74: tmnxOverlayFabricFailure properties..... | 70 |
| Table 75: tmnxOverlayFabricPartialFailure properties..... | 70 |
| Table 76: tmnxOverlayFabricStatus properties..... | 71 |

1 Getting started

Find general information about this guide.

1.1 About this guide

This guide provides descriptions of event notifications that are forwarded to a destination such as a file or an SNMP trap. Properties that are reported include alarm or raising event name, raising condition, and clearing event information. The information is intended to assist with identifying and responding to the event notifications.

Command outputs shown in this guide are examples only; actual displays may differ depending on supported functionality and user configuration.

The CLI trees and command descriptions can be found in the *MAG-c CLI Reference Guide*.



Note: This guide generically covers content for the release specified on the title page of the guide, and may also contain some content that will be released in later maintenance loads. See the applicable *MAG-c Release Notes* for information about features supported in each load of the software release.



Note: The information in this guide is intended to be used in conjunction with the SR OS software user guides. The SR OS software user guides describe SR OS service features that are supported by the MAG-c. See the *7450 ESS, 7750 SR, 7950 XRS, and VSR Documentation Suite Overview Card 20.10.R1* for specific guide titles.

1.2 Conventions

This section describes the general conventions used in this guide.

1.2.1 Precautionary and information messages

The following information symbols are used in the documentation.



DANGER: Danger warns that the described activity or situation may result in serious personal injury or death. An electric shock hazard could exist. Before you begin work on this equipment, be aware of hazards involving electrical circuitry, be familiar with networking environments, and implement accident prevention procedures.



WARNING: Warning indicates that the described activity or situation may, or will, cause equipment damage, serious performance problems, or loss of data.



Caution: Caution indicates that the described activity or situation may reduce your component or system performance.



Note: Note provides additional operational information.



Tip: Tip provides suggestions for use or best practices.

1.2.2 Options or substeps in procedures and sequential workflows

Options in a procedure or a sequential workflow are indicated by a bulleted list. In the following example, at step 1, the user must perform the described action. At step 2, the user must perform one of the listed options to complete the step.

Example: Options in a procedure

1. User must perform this step.
2. This step offers three options. User must perform one option to complete this step.
 - This is one option.
 - This is another option.
 - This is yet another option.

Substeps in a procedure or a sequential workflow are indicated by letters. In the following example, at step 1, the user must perform the described action. At step 2, the user must perform two substeps (a. and b.) to complete the step.

Example: Substeps in a procedure

1. User must perform this step.
2. User must perform all substeps to complete this action.
 - a. This is one substep.
 - b. This is another substep.

2 Log events overview

Log events have common elements or properties but are formatted in a way appropriate for the specific destination whether recorded to a file or sent as an SNMP trap.

Logs can be directed to memory, a console, a session, a local file, a syslog server, or an SNMP manager. All application-generated events have the following properties:

- a time stamp in UTC or local time
- the generating application
- a unique event ID within the application
- a router name identifying the VRF-ID that generated the event
- a subject identifying the affected object
- a short text description

See the associated SNMP notification definition in the SR OS MIBs for more information about the variables found in the message format strings.

The general format for a log event with either a memory, console, or file destination is as follows:

```
nnnn YYYY/MM/DD HH:MM:SS.SS TZONE <severity>: <application> #<event_id> <router-name>
<subject>
<message>
```

The following is a log event example:

```
252 2013/05/07 16:21:00.76 UTC WARNING: SNMP #2005 Base my-interface-abc
"Interface my-interface-abc is operational"
```

The following table lists the specific elements that compose the general format.

Table 1: Log entry field descriptions

| Label | Description |
|-------------|--|
| nnnn | The log entry sequence number |
| YYYY/MM/DD | The UTC or local date stamp for the log entry YYYY Year MM Month DD Date |
| HH:MM:SS.SS | The UTC time stamp for the event HH Hours (24-hour format) MM Minutes SS.SS Seconds |

| Label | Description |
|---------------|--|
| TZONE | The time zone (for example, UTC, EDT) as configured by the configure log log-id x time-format command |
| <severity> | The severity level of the event <ul style="list-style-type: none"> • CRITICAL • MAJOR • MINOR • WARNING • INFO • CLEARED |
| <application> | The name of the application generating the log message |
| <event_id> | The application's event ID number for the event |
| <router> | The router name representing the VRF-ID that generated the event; some examples include: Base, management, and vprn348 |
| <subject> | The subject or affected object for the event |
| <message> | A text description of the event |

The following table lists the sources that trigger an event.

Table 2: Log event sources

| Event source | Description |
|-----------------|--|
| Security events | Events pertaining to attempts to breach system security |
| Change events | Events pertaining to the configuration and operation of the node |
| Main events | Events pertaining to applications that are not assigned to other event categories or sources |
| Debug events | Events pertaining to trace or other debugging information |

2.1 Viewing log events

- View all the log events.

```
show log event-control
```

**Note:**

- You can use this command and specify an application (for example, subscriber management).
- When an L precedes an event, it indicates that this event does not generate an SNMP notification.
- The event severity can be modified whether the event is generated or dropped.
- The severity of an SNMP trap is assigned by the SNMP manager.
- By default, all events are throttled at 2000 per second. System throttle or event-specific throttle can be modified.
- A maximum of 100 log IDs can be configured and filters can be used to specify the application, event ID, event severity, forward or drop the matching event, and so on, by applying those to a set of logs. Each log ID is configured by specifying an event source and the log destination.



Note: Logs with ID 99 and 100 are default logs directed to memory that contain the main events. The log with ID 100 has a filter applied to match events with severity greater than or equal to major.

Example

```
show log event-control
=====
Log Events
=====
Application
ID#      Event Name                               P    g/s    Logged    Dropped
-----
APPLICATION_ASSURANCE:
  4401 tmnxBsxIsaAaGrpFailureV2             MA   thr    0         0
  4402 tmnxBsxIsaAaGrpFailureClearV2       WA   thr    0         0
<snip>
MOBILE_GATEWAY:
  2001 tmnxMobGwPathMgmtPeerState          WA   thr    0         0
  2002 tmnxMobGwDiameterPeerState          WA   thr    0         0
L 2003 tmnxMobGwCpmRestartUpdate           WA   thr    0         0
...
...
...
=====
```

- View a specific log event.

```
show log log-id log-id
```

Example

```
show log log-id 99
=====
Event Log 99
=====
Description : Default System Log
Memory Log contents [size=500 next event=183 (not wrapped)]
182 2017/09/12 18:46:25.66 EDT WARNING: SNMP #2005 Base xyz
"Interface xyz is operational"
```

```
181 2017/09/12 18:45:53.97 EDT WARNING: SNMP #2005 Base system
"Interface system is operational"
```

- View the log collector information.

```
show log log-collector
```

Example

```
show log log-collector
=====
Log Collectors
=====
Main                               Logged : 191                               Dropped : 0
  Dest Log Id: 99                   Filter Id: 0                               Status: enabled                            Dest Type: memory
  Dest Log Id: 100                  Filter Id: 1001                            Status: enabled                            Dest Type: memory
  Dest Log Id: 90                   Filter Id: 0                               Status: enabled                            Dest Type: snmp
  Dest Log Id: 20                   Filter Id: 100                             Status: enabled                            Dest Type: file
  Dest Log Id: 5                    Filter Id: 0                               Status: enabled                            Dest Type: syslog
Security                             Logged : 28                               Dropped : 0
  Dest Log Id: 90                   Filter Id: 0                               Status: enabled                            Dest Type: snmp
  Dest Log Id: 20                   Filter Id: 100                             Status: enabled                            Dest Type: file
  Dest Log Id: 5                    Filter Id: 0                               Status: enabled                            Dest Type: syslog
Change                             Logged : 451                               Dropped : 0
  Dest Log Id: 90                   Filter Id: 0                               Status: enabled                            Dest Type: snmp
  Dest Log Id: 20                   Filter Id: 100                             Status: enabled                            Dest Type: file
  Dest Log Id: 5                    Filter Id: 0                               Status: enabled                            Dest Type: syslog
Debug                               Logged : 0                               Dropped : 0
LI                                  Logged : 65                               Dropped : 0
=====
```

- Create and configure filters.

```
configure log filter filter-id
```



Note: The MAG-c also supports log events generated by the 7750 SR OS. See the SR OS documentation for more information about the SNMP notifications from SR OS.

2.2 Log event configuration

2.2.1 Configuring SNMP as the log destination

You can specify SNMP as the destination for log events.

About this task

The MAG-c supports SNMPv1, SNMPv2, and SNMPv3 with the underlying system being based on SNMPv3. SNMPv1 and SNMPv2 are implemented by creating communities based on SNMPv3. Logical objects, for example VPRNs and interfaces, are assigned an index during the boot sequence based on their order in the configuration file. To maintain this index after a reboot, SNMP persistence must be enabled in the BOF. When enabled, and an **admin save** command is issued, the persistent indexes are stored in a `.ndx` file, which has the same name as the configuration file.

Procedure

Step 1. Enable persistent indexes in the BOF.

```
bof persist on
```

Step 2. Save the BOF.

```
bof save
```

Step 3. Configure the SNMP packet size.

```
configure system snmp packet-size bytes
```

Example

```
configure system snmp packet-size 9212
```

Step 4. Enable SNMP.

```
configure system snmp no shutdown
```

Step 5. Configure an SNMP community.

```
configure system security snmp community community-string access-permissions
version version
```

Example

```
configure system security snmp community test rwa version v2c
```

Step 6. Save the configuration.

```
admin save
```

Step 7. View the SNMP status.

```
show system information
```

If the SNMP configuration is successful, the **SNMP Index Boot Status** field in the output of the command must indicate **Persistent**.

Example

```
# show system information
=====
System Information
=====
System Name       : cses-V20
System Type       : 7750 SR-12
Chassis Topology  : Standalone
System Version    : B-0.0.I2946
System Contact    :
System Location   :
System Coordinates :
System Active Slot : A
System Up Time    : 64 days, 18:33:04.70 (hr:min:sec)
```

```

Configuration-mode      : classic
Configuration-oper-mode: classic
SNMP Port               : 161
SNMP Engine ID         : 0000197f0000d814ff000000
SNMP Engine Boots      : 1
SNMP Max Message Size  : 1500
SNMP Admin State       : Enabled
SNMP Oper State        : Enabled
SNMP Index Boot Status : Persistent
SNMP Sync State        : N/A
...
...
=====

```

Step 8. View the SNMP counters used for requests, responses, and traps.

```
show snmp counters
```

Example

```

# show snmp counters
=====
SNMP counters:
=====
  in packets : 107
-----
  in gets : 46
  in getnexts : 0
  in getbulks : 0
  in sets : 61
  out packets: 107
-----
  out get responses : 107
  out traps : 0
  variables requested: 24
  variables set : 84
-----
  Failed requests due to lock being taken by netconf
  failed sets : 0
=====

```

2.2.2 Configuring an SNMP trap destination

An SNMP trap destination is a log with SNMP set as the destination.

About this task

In this example, the SNMP trap is configured as follows:

- log ID 90
- target name set to “manager”
- IP address 192.0.2.255
- SNMP version SNMPv2
- community name set to “community”

Procedure

Step 1. Create an SNMP trap group.

```
configure log snmp-trap-group log-id
```

Example

```
configure log snmp-trap-group 90
```

Step 2. Configure the SNMP trap group.

```
snmp-trap-group log-id trap-target name address ip-address [snmpv1|snmpv2|snmpv3]
  notify-community communityName|snmpv3SecurityName
```

Example

```
snmp-trap-group 90 trap-target "manager" address 192.0.2.255 snmpv2c notify-community
  community
```

Step 3. Create a log ID.

```
configure log log-id
```

Use the log ID configured for the SNMP trap group in step 1.

Example

```
configure log 90
```

Step 4. Configure the log ID.

```
log-id log-id to snmp size
```

Specify SNMP as the destination and the number of events.

Example

```
log-id 90 to snmp 3000
```

Step 5. View the configured SNMP trap destination.

```
show log snmp-trap-group log-id
```

Example

```
# show log snmp-trap-group 90
=====
SNMP Trap Groups
=====
id      name
port    address
-----
90      manager
162     192.0.2.255
=====
```



Note: By default, Nokia NSP NFM-P uses log ID 98.

2.2.3 Configuring a file as the log destination

You can specify a file as the log destination.

About this task

The filename follows the format `logeff-timestamp`, where:

| | |
|-----------------|------------------------------------|
| <code>ee</code> | The log ID (<i>log-id</i>) |
| <code>ff</code> | The file ID (<i>log-file-id</i>) |

In this example, the destination file is configured as follows:

- file ID 10
- storage location CF1:
- rollover of records 1440 minutes and retention 168 hours
- linked to log ID 20, which receives event logs from the main, security, and changed source streams (see [Table 2: Log event sources](#))
- log ID 20 directed to file ID 10

Procedure

Step 1. Create a log file.

```
configure log file-id log-file-id
```

Example

```
configure log file-id 10
```

Step 2. Configure the storage location of the log file.

```
configure log file-id log-file-id location
```

Example

```
configure log file-id 10 location cf1:
```

Step 3. Configure the rollover and retention duration of the log file.

```
configure log file-id log-file-id rollover minutes [retention] hours
```

Example

```
configure log file-id 10 rollover 1440 retention 168
```

Step 4. Create a log ID.

```
configure log log-id
```

Example

```
configure log 20
```

Step 5. Configure the source streams for the log ID.

```
configure log log-id from
```

Example

```
configure log 20 from main security change
```

Step 6. Configure the destination type of the log.

```
configure log log-id to file log-file-id
```

Example

```
configure log 20 to file 10
```

2.2.4 Configuring a syslog as the log destination

You can specify a syslog as the log destination.

About this task

In this example, the syslog is configured as follows:

- syslog ID 5
- syslog host address 10.10.1.1
- linked to log ID 5, which receives event logs from the main, security, and changed source streams (see [Table 2: Log event sources](#))

Procedure**Step 1.** Create a syslog.

```
configure log syslog syslog-id
```

Example

```
configure log syslog 5
```

Step 2. Configure the storage location of the syslog.

```
configure log syslog syslog-id address ip-address
```

Example

```
configure log syslog 5 address 10.10.1.1
```

Step 3. Create a log ID.

```
configure log log-id
```

Example

```
configure log 5
```

Step 4. Configure the source streams for the log ID.

```
configure log log-id from
```

Example

```
configure log 5 from main security change
```

Step 5. Configure the destination type of the log ID.

```
configure log log-id to syslog syslog-id
```

Example

```
configure log 5 to syslog 5
```

2.2.5 Debugging an application

You can debug an application using a log with the debug trace specified as the event source. Although you can debug an application in the current session window, using a log as the destination is more useful for reviewing the log.

About this task



Note: The steps in this section only describe the procedure for configuring a log file that stores the output of debug commands. See the *MAG-c Control Plane Function Guide* for more information about how to enable and use the **call-insight** and PDN **debug** commands.

In this example, application debugging is configured as follows:

- file ID 10
- storage location CF2:
- linked to log ID 30, which receives event logs from the debug trace (see [Table 2: Log event sources](#))
- log ID 30 directed to file ID 10



Caution: Debug commands must be used with caution. Nokia recommends disabling debugging after any debug operation has been finished. The **no debug** command disables all the enabled debug commands.

Procedure

Step 1. Create a log file.

```
configure log file-id log-file-id
```

Example

```
configure log file-id 10
```

Step 2. Configure the storage location of the log file.

```
configure log file-id log-file-id location
```

Example

```
configure log file-id 10 location cf2:
```

Step 3. Create a log ID.

```
configure log log-id
```

Example

```
configure log 30
```

Step 4. Configure the source stream for the log ID.

```
configure log log-id from
```

Example

```
configure log 30 from debug-trace
```

Step 5. Configure the destination type of the log.

```
configure log log-id to file log-file-id
```

Example

```
configure log 30 to file 10
```

2.3 Sample log event

In this guide, each log event is described in a separate table.

The following table contains a sample log event entry for the `tmnxMobGwBngLockoutLimitExceeded` log event.

Table 3: *tmnxMobGwBngLockoutLimitExceeded* properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2007 |
| Event name | tmnxMobGwBngLockoutLimitExceeded |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.120 |
| Default severity | warning |
| Source stream | main |
| Message format string | The maximum number of BNG sessions in locked-out or monitored state is exceeded <i>\$tmnxMobGwNtfyInformation\$</i> |
| Cause | While the maximum number of BNG sessions in monitored or locked-out state is in use, a new session must be monitored or locked out. |
| Effect | Another session being monitored or locked out is prematurely released to accommodate the new session. |
| Recovery | Recovery is not necessary. |

The table title for a log event entry is the event name. Each entry contains the information described in the following table.

Table 4: *Log entry field descriptions*

| Label | Description |
|----------------------------------|--|
| Application name | The name of the application generating the log message |
| Event ID | The application event ID number for the event |
| Event name | The name of the event |
| SNMP notification prefix and OID | The prefix and OID of the SNMP notification associated with the log event |
| Default severity | The default severity level of the event <ul style="list-style-type: none"> • CRITICAL • MAJOR • MINOR • WARNING • INFO • CLEARED |

| Label | Description |
|-----------------------|--|
| Source stream | The event source <ul style="list-style-type: none">• main• security• change• debug See Table 2: Log event sources for more information. |
| Message format string | A text description of the event |
| Cause | The cause of the event |
| Effect | The effect of the event |
| Recovery | How to recover from this event, if necessary |

3 Log events

Get a summary of the supported alarms and raising events and detailed descriptions per alarm and event object.

3.1 MC_REDUNDANCY

3.1.1 tmnxMcMobileBothLockedToMaster

Table 5: *tmnxMcMobileBothLockedToMaster* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MC_REDUNDANCY |
| Event ID | 5002 |
| Event name | tmnxMcMobileBothLockedToMaster |
| SNMP notification prefix and OID | TIMETRA-MC-REDUNDANCY-MIB.tmnxMcMobRedundancy Notifications.6 |
| Default severity | minor |
| Source stream | main |
| Message format string | For peers <i>\$tmnxMcPeerIpAddrForNotify\$</i> and <i>\$tmnxMcPeerSrcIpAddr\$</i> both nodes locked to the active operational role |
| Cause | A misconfiguration occurred because enabling the mc-master-lock on both the primary and secondary geo-redundancy nodes is only permitted when the mc-mobile link between these nodes is down, and both nodes have assumed the active operational role. When the mc-mobile link is restored (reaches the UP state), the system triggers a tmnxMcMobileBothLockedToMaster notification indicating that both the primary and secondary nodes are locked in the active operational role. However, when the mc-mobile link between the geo-redundancy nodes is operationally UP and peering is successful, the mc-master-lock CLI configuration is restricted to the node with the active operational role. |
| Effect | The geo-redundancy link is not established because peering of these nodes is not possible. |
| Recovery | Diagnose and fix the mc-master-lock misconfiguration. |

3.1.2 tmnxMcMobileGeoRedChgInfo

Table 6: tmnxMcMobileGeoRedChgInfo properties

| Property name | Value |
|----------------------------------|---|
| Application name | MC_REDUNDANCY |
| Event ID | 2040 |
| Event name | tmnxMcMobileGeoRedChgInfo |
| SNMP notification prefix and OID | TIMETRA-MC-REDUNDANCY-MIB.tmnxMcMobRedundancy Notifications.2 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- \$tmnxMcPeerMobileMGId\$, Src Address- \$tmnxMcPeerSrcIpAddr\$, CPM Geo-Red State-\$tmnxMcPeerMobileMGCPMGeoRedState\$, Mob GW Geo Red State- \$tmnxMcPeerMobileMGGeoRedState\$, Number of Hot Groups-\$tmnxMcPeerMobileMGNumHotGroups\$ (\$tmnxMcPeerMGHotGroupList\$), Number Of Warm Groups- \$tmnxMcPeerMobileMGNumWarmGroups\$ (\$tmnxMcPeerMGWarmGroupList\$), Number Of Cold Groups-\$tmnxMcPeerMobileMGNumColdGroups\$ (\$tmnxMcPeerMGColdGroupList\$), Peer Address-\$tmnxMcPeerIpAddr\$, Peer State-\$tmnxMcPeerMobileMGPeerState\$, Peer State Reason- \$tmnxMcPeerMobileMGPeerStChgRsn\$ |
| Cause | The chassis or the CPM changed its geo-redundancy state, or the peer connection status changed. |
| Effect | If the chassis or CPM state changes to cold or warm, or the peer state is disconnected, the system is no longer in a geo-redundant state. |
| Recovery | Diagnose the cause of the state change, restore the UP state for the peer, the peer link, or both, and ensure the chassis and the CPM geo-redundancy are in the hot state. |

3.1.3 tmnxMcMonitorMclcrAlarm

Table 7: tmnxMcMonitorMclcrAlarm properties

| Property name | Value |
|------------------|---------------|
| Application name | MC_REDUNDANCY |
| Event ID | 5001 |

| Property name | Value |
|----------------------------------|---|
| Event name | tmnxMcMonitorMclcrAlarm |
| SNMP notification prefix and OID | TIMETRA-MC-REDUNDANCY-MIB.tmnxMcMobRedundancyNotifications.5 |
| Default severity | minor |
| Source stream | main |
| Message format string | The monitor-mc-icr alarm occurred on interface <i>\$vRtrIfIndex\$</i> for the reason <i>\$tmnxMcMonitorMclcrAlarmRsnCode\$</i> . |
| Cause | The alarm was generated with the following reason codes: 1. 'tmnxMcMonitorMclcrAlarmRsnCode trafficDetected' - the reference point traffic detected on the standby node reaches the configured monitor-mc-redirect high threshold vRtrIfMonMcRedirectHighThresh. 2. 'tmnxMcMonitorMclcrAlarmRsnCode trafficCleared' - the reference point traffic is below the configured monitor-mc-redirect low threshold vRtrIfMonMcRedirectLowThresh. |
| Effect | A network configuration issue or a partial network failure is detected. |
| Recovery | Diagnose and fix the issue or the partial network failure. |

3.2 MOBILE_CUPS_BNG

3.2.1 tmnxMobBngStaticSeOperStateUp

Table 8: *tmnxMobBngStaticSeOperStateUp* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2012 |
| Event name | tmnxMobBngStaticSeOperStateUp |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.150 |
| Default severity | warning |
| Source stream | main |
| Message format string | Static session <i>\$tmnxMobGwNtfySessionName\$</i> is <i>\$tmnxMobGwNtfyTruthValue\$</i> operational |
| Cause | The operational state of a static CUPS BNG session changed. |

| Property name | Value |
|---------------|---|
| Effect | When the operational state of a static CUPS BNG session is down, the system disconnects the user associated with the session. |
| Recovery | The recovery action depends on the cause. |

3.2.2 tmnxMobGwBngLockoutLimitExceeded

Table 9: *tmnxMobGwBngLockoutLimitExceeded* properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2007 |
| Event name | tmnxMobGwBngLockoutLimitExceeded |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.120 |
| Default severity | warning |
| Source stream | main |
| Message format string | The maximum number of BNG sessions in locked-out or monitored state is exceeded <i>\$tmnxMobGwNtfyInformation\$</i> |
| Cause | A new session is monitored or locked out when the maximum number of monitored or locked-out BNG sessions is already in use. |
| Effect | The system prematurely releases a currently monitored or locked-out BNG session to accommodate the new session. |
| Recovery | Recovery is not necessary. |

3.2.3 tmnxMobGwBngNatPrefixRevocation

Table 10: *tmnxMobGwBngNatPrefixRevocation* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2009 |
| Event name | tmnxMobGwBngNatPrefixRevocation |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.133 |

| Property name | Value |
|-----------------------|---|
| Default severity | minor |
| Source stream | main |
| Message format string | CUPS BNG NAT Prefix revocation : MSCP <i>\$tmnxMobGwNtfyMscpld</i> \$ Realm <i>\$tmnxMobGwNtfyNwRealmName\$</i> pool <i>\$tmnxMobGwNtfyPoolName\$</i> Gw <i>\$tmnxMobGwNtfyGatewayId\$</i> , UP <i>\$tmnxMobGwNtfyUpPeerAddress\$</i> , prefix <i>\$tmnxMobGwNtfyAddr\$</i> / <i>\$tmnxMobGwNtfyPfxLength\$</i> , reason ' <i>\$tmnxMobGwNtfyRevocationReason\$</i> ' |
| Cause | An error occurred during a NAT audit between MSCP and OAM or MSCP and ODSA, and the system cannot acknowledge the prefix. |
| Effect | The session is deleted. [RECOVERY] |
| Recovery | N/A |

3.2.4 tmnxMobGwBngResFsgUpfChange

Table 11: *tmnxMobGwBngResFsgUpfChange* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2010 |
| Event name | tmnxMobGwBngResFsgUpfChange |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.134 |
| Default severity | warning |
| Source stream | main |
| Message format string | UP resiliency: UP change: Gw <i>\$tmnxMobGwNtfyGatewayId\$</i> , UP group <i>\$tmnxMobGwNtfyCupsBngUpGroup\$</i> , FSG <i>\$tmnxMobGwNtfyFsgId\$</i> , primary UP <i>\$tmnxMobGwNtfyUpf1\$</i> (health <i>\$tmnxMobGwNtfyUpf1Health\$</i>), secondary UP <i>\$tmnxMobGwNtfyUpf2\$</i> (health <i>\$tmnxMobGwNtfyUpf2Health\$</i>), previous primary UP <i>\$tmnxMobGwNtfyUpf1Prev\$</i> , previous secondary UP <i>\$tmnxMobGwNtfyUpf2Prev\$</i> |
| Cause | The value changed for TIMETRA-MOBILE-PDN-CUPS-MIB::tmnxMobPdnBngResFsgActUpf or TIMETRA-MOBILE-PDN-CUPS-MIB::tmnxMobPdnBngResFsgStdbypf. |
| Effect | If the primary UPF changes, the traffic associated with this fate sharing group (FSG) goes through another UPF. If the secondary UPF changes and the pair is in hot-standby mode, another UPF tracks the session state. . |

| Property name | Value |
|---------------|-----------------------------------|
| Recovery | No recovery actions are required. |

3.2.5 tmnxMobGwBngResFsgUpfError

Table 12: tmnxMobGwBngResFsgUpfError properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2011 |
| Event name | tmnxMobGwBngResFsgUpfError |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.149 |
| Default severity | warning |
| Source stream | main |
| Message format string | UP resiliency: UP error: Gw \$tmnxMobGwNtfyGatewayId\$, UP group \$tmnxMobGwNtfyCupsBngUpGroup\$, FSG \$tmnxMobGwNtfyFsgId\$, \$tmnxMobGwNtfyTruthValue\$ UP \$tmnxMobGwNtfyUpf1\$: \$tmnxMobGwNtfyError\$\$tmnxMobGwNtfyInformation\$ |
| Cause | The UP reported an error when the system, acting as a CUPS Control Plane (CP), requested a UP to modify (create, delete, or change) an FSG. |
| Effect | If the UP is active for the FSG, the system transfers the active role to the previously active UP. |
| Recovery | No recovery actions are required. |

3.2.6 tmnxMobGwBngSessCreateUpfNonResp

Table 13: tmnxMobGwBngSessCreateUpfNonResp properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2002 |
| Event name | tmnxMobGwBngSessCreateUpfNonResp |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.106 |

| Property name | Value |
|-----------------------|---|
| Default severity | minor |
| Source stream | main |
| Message format string | CUPS BNG Session create UP non-response for: Gw \$tmnxMobGwNtfyGatewayId\$, VRtr \$tmnxMobGwNtfyVrtrId\$, UP \$tmnxMobGwNtfyUpPeerAddress\$, node-ID \$tmnxMobGwNtfyPeerNodeId\$, session key: L2-access-id \$tmnxMobGwNtfyCupsBngSessKeyL2Acc\$, s-vlan \$tmnxMobGwNtfyCupsBngSessKeySVlan\$, c-vlan \$tmnxMobGwNtfyCupsBngSessKeyCVlan\$, mac \$tmnxMobGwNtfyCupsBngSessKeyMac\$, circuit-id '0x\$tmnxMobGwNtfyCupsBngSessKeyCirlId\$', remote-id '0x \$tmnxMobGwNtfyCupsBngSessKeyRemId\$' |
| Cause | The UP did not send a response message to acknowledge a Create Session Request. |
| Effect | The CP cancels the session setup and the UP may have a lingering session state. |
| Recovery | The operator's assistance is needed to remove any session state lingering on the UP. |

3.2.7 tmnxMobGwBngSessDuplAttr

Table 14: tmnxMobGwBngSessDuplAttr properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2008 |
| Event name | tmnxMobGwBngSessDuplAttr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.132 |
| Default severity | minor |
| Source stream | main |
| Message format string | CUPS BNG Session setup duplicate session identification attribute detected: Gw \$tmnxMobGwNtfyGatewayId\$, VRtr \$tmnxMobGwNtfyVrtrId\$, UP \$tmnxMobGwNtfyUpPeerAddress\$, node-ID \$tmnxMobGwNtfyPeerNodeId\$, L2-access-id \$tmnxMobGwNtfyCupsBngSessKeyL2Acc\$, s-vlan \$tmnxMobGwNtfyCupsBngSessKeySVlan\$, c-vlan \$tmnxMobGwNtfyCupsBngSessKeyCVlan\$, mac \$tmnxMobGwNtfyCupsBngSessKeyMac\$, circuit-id '0x\$tmnxMobGwNtfyCupsBngSessKeyCirlId\$', remote-id '0x \$tmnxMobGwNtfyCupsBngSessKeyRemId\$', up-group '\$tmnxMobGwNtfyCupsBngUpGroup\$' |

| Property name | Value |
|---------------|--|
| Cause | A session setup used attributes that conflict with unique session identification attributes, or attribute combinations of other active sessions. |
| Effect | The session is not available for external targeting based on session attribute identification. |
| Recovery | In case external targeting capability is required, the operator's assistance is needed to clear the session. |

3.2.8 tmnxMobGwBngSessTermBySystem

Table 15: tmnxMobGwBngSessTermBySystem properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2001 |
| Event name | tmnxMobGwBngSessTermBySystem |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.105 |
| Default severity | warning |
| Source stream | main |
| Message format string | CUPS BNG session terminated by the system: Reason <i>\$tmnxMobGwNtfyCupsBngSessTermReas\$</i> , extra info ' <i>\$tmnxMobGwNtfyCupsBngSessTermInfo\$</i> ', Gw <i>\$tmnxMobGwNtfyGatewayId\$</i> , VRtr <i>\$tmnxMobGwNtfyVrtrId\$</i> , UP-ip <i>\$tmnxMobGwNtfyUpPeerAddress\$</i> , L2-access-id <i>\$tmnxMobGwNtfyCupsBngSessKeyL2Acc\$</i> , s-vlan <i>\$tmnxMobGwNtfyCupsBngSessKeySVlan\$</i> , c-vlan <i>\$tmnxMobGwNtfyCupsBngSessKeyCVlan\$</i> , mac <i>\$tmnxMobGwNtfyCupsBngSessKeyMac\$</i> , circuit-id '0x <i>\$tmnxMobGwNtfyCupsBngSessKeyCirId\$</i> ', remote-id '0x <i>\$tmnxMobGwNtfyCupsBngSessKeyRemId\$</i> ', up-group ' <i>\$tmnxMobGwNtfyCupsBngUpGroup\$</i> ' |
| Cause | The system found a reason indicated by tmnxMobGwNtfyCupsBngSessTermReas for terminating a session. |
| Effect | The established session is terminated or the session being set up is cancelled. |
| Recovery | None. |

3.2.9 tmnxMobGwBngSubscriberCreate

Table 16: tmnxMobGwBngSubscriberCreate properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2003 |
| Event name | tmnxMobGwBngSubscriberCreate |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.111 |
| Default severity | warning |
| Source stream | main |
| Message format string | CUPS BNG new subscriber created: Sub-Id ' <i>\$tmnxMobGwNtfyCupsBngSubId\$</i> ', externally assigned alias (if any) ' <i>\$tmnxMobGwNtfyCupsBngSubExtAlias\$</i> ', UP IP <i>\$tmnxMobGwNtfyAddr\$</i> |
| Cause | A session setup, for which there wasn't any subscriber state yet, is successful. |
| Effect | The subscriber state is created. |
| Recovery | Not applicable. |

3.2.10 tmnxMobGwBngSubscriberDelete

Table 17: tmnxMobGwBngSubscriberDelete properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_CUPS_BNG |
| Event ID | 2004 |
| Event name | tmnxMobGwBngSubscriberDelete |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.112 |
| Default severity | warning |
| Source stream | main |
| Message format string | CUPS BNG subscriber deleted: Sub-Id ' <i>\$tmnxMobGwNtfyCupsBngSubId\$</i> ', externally assigned alias (if any) ' <i>\$tmnxMobGwNtfyCupsBngSubExtAlias\$</i> ', UP IP <i>\$tmnxMobGwNtfyAddr\$</i> |

| Property name | Value |
|---------------|--|
| Cause | The last session of an active subscriber was terminated. |
| Effect | The subscriber state is deleted. |
| Recovery | Not applicable. |

3.3 MOBILE_GATEWAY

3.3.1 tmnxMcRedundancyTrafficReceived

Table 18: *tmnxMcRedundancyTrafficReceived* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2084 |
| Event name | tmnxMcRedundancyTrafficReceived |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.82 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Ref point- <i>\$tmnxMobGwNtfyRefPointType\$</i> , RefPointName- <i>\$tmnxMobGwNtfyRefPointName\$</i> , InterfaceType- <i>\$tmnxMobGwNtfyIfType\$</i> . |
| Cause | Traffic was detected at the ICR node because of a network issue. |
| Effect | Traffic coming to the ICR node is dropped if shunting is not used, or forwarded accordingly if shunting is used. |
| Recovery | Check the cause of the routing change in the network, and fix it if possible. If the traffic cannot be directed back, but the routing works towards the node, perform an ICR switchover. |

3.3.2 tmnxMobDbRedRoleActive

Table 19: *tmnxMobDbRedRoleActive* properties

| Property name | Value |
|------------------|----------------|
| Application name | MOBILE_GATEWAY |

| Property name | Value |
|----------------------------------|--|
| Event ID | 2151 |
| Event name | tmnxMobDbRedRoleActive |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.153 |
| Default severity | warning |
| Source stream | main |
| Message format string | Database <i>\$tmnxMobDbId\$</i> with IP address <i>\$tmnxMobDbIpAddr\$</i> is now active |
| Cause | The redundancy role of a database changed from standby to active. |
| Effect | The database is actively used. |
| Recovery | Not applicable. |

3.3.3 tmnxMobDbStatusChanged

Table 20: *tmnxMobDbStatusChanged* properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2152 |
| Event name | tmnxMobDbStatusChanged |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.154 |
| Default severity | minor |
| Source stream | main |
| Message format string | Database <i>\$tmnxMobDbId\$</i> with IP address <i>\$tmnxMobDbIpAddr\$</i> is now <i>\$tmnxMobDbStatus\$</i> |
| Cause | The state of a database changed. |
| Effect | When the new state is 'up', the connection with the database is available. When the new state is 'down', the connection with the database is not available. |
| Recovery | If the new state is 'down' and there is no subsequent 'tmnxMobDbRedRoleActive' notification, an ICR switchover is recommended. |

3.3.4 tmnxMobGwApnMaxAttachLmtAlrm

Table 21: tmnxMobGwApnMaxAttachLmtAlrm properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2124 |
| Event name | tmnxMobGwApnMaxAttachLmtAlrm |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.124 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , APN Name- <i>\$tmnxMobGwNtfyApnName\$</i> , attach request rate reached maximum limit. |
| Cause | The GTP-based attach rate exceeded the configurable max-session-attach limit for tmnxMobGwNtfyApnName. |
| Effect | If there is a new GTP-based attach session and the attach rate has been exceeded, the new attach session is rejected. |
| Recovery | The alarm will be cleared when the rate goes back below the max-session-attach limit value. |

3.3.5 tmnxMobGwApnMaxAttachLmtAlrmClr

Table 22: tmnxMobGwApnMaxAttachLmtAlrmClr properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2125 |
| Event name | tmnxMobGwApnMaxAttachLmtAlrmClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.125 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , APN Name- <i>\$tmnxMobGwNtfyApnName\$</i> , attach request rate goes below maximum limit. |

| Property name | Value |
|---------------|--|
| Cause | The GTP-based attach rate dropped below the configurable max-session-attach limit for this tmnxMobGwNtfyApnName. |
| Effect | The GTP-based attach rate drops below the configured max-session-attach limit value. |
| Recovery | No further action is required. |

3.3.6 tmnxMobGwAssociationPeerState

Table 23: tmnxMobGwAssociationPeerState properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2075 |
| Event name | tmnxMobGwAssociationPeerState |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.73 |
| Default severity | minor |
| Source stream | main |
| Message format string | Association state changed to <i>\$tmnxMobGwNtfyPeerAssociatnState\$</i> for <i>\$tmnxMobGwNtfySigPlane Type\$</i> Peer <i>\$tmnxMobGwNtfyPeerNode Id\$</i> on GW <i>\$tmnxMobGwNtfyGatewayId\$</i> Reference Point <i>\$tmnxMobGwNtfyRefPointType\$ \$tmnxMobGwNtfyRefPointName\$</i> (IP Address: <i>\$tmnxMobGwNtfyRfPtPeerAddr\$</i>). Recovery Time: <i>\$tmnxMobGwNtfyRecoveryTimestamp\$</i> cp func <i>\$tmnxMobGwNtfyPeerCPFuncFeatures\$</i> up func <i>\$tmnxMobGwNtfyPeerUPFuncFeatures\$</i> bbfunc <i>\$tmnxMobGwNtfyPeerBbfUPFuncFeats\$</i> |
| Cause | The Association state changed when the association is set up or released. The association can be set up or released by association-related node-level messages triggered by either the gateway or the peer. The gateway initiates Association Messages if the peer is configured in the association peer list. |
| Effect | Path management for PFCP peers and UPF selection can occur after the association is established. Path management or UPF selection does not happen if the association state is down. |
| Recovery | If the association state is down when the gateway initiates a release, the gateway state must come up for the association to be reestablished. If the release was initiated by the peer, the peer triggers the setup when it comes up again. |

3.3.7 tmnxMobGwAssocNodeIdFail

Table 24: tmnxMobGwAssocNodeIdFail properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2121 |
| Event name | tmnxMobGwAssocNodeIdFail |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.121 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw - \$tmnxMobGwNtfyGatewayId\$, epc-node not configured for \$tmnxMobGwPdnNtfySxAssociation\$ |
| Cause | A PFCP Association Setup procedure failed because of a missing node ID. |
| Effect | The PFCP Association Setup procedure continues to fail while the node ID is missing. |
| Recovery | Configure a valid string for the configure mobile-gateway pdn epc-node command. |

3.3.8 tmnxMobGwAssocNodeIdFailClr

Table 25: tmnxMobGwAssocNodeIdFailClr properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2123 |
| Event name | tmnxMobGwAssocNodeIdFailClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.123 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw - \$tmnxMobGwNtfyGatewayId\$, configured epc-node re-established for \$tmnxMobGwPdnNtfySxAssociation\$ |

| Property name | Value |
|---------------|---|
| Cause | PFCP Association Setup re-established after the node ID became available. |
| Effect | There is no effect for this notification. |
| Recovery | No further action is required. |

3.3.9 tmnxMobGwAssocNodeIdMismatch

Table 26: *tmnxMobGwAssocNodeIdMismatch* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2143 |
| Event name | tmnxMobGwAssocNodeIdMismatch |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.143 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw - \$tmnxMobGwNtfyGatewayId\$, node ID mismatched for \$tmnxMobGwPdnNtfySxAssociation\$ PFCP association setup |
| Cause | A PFCP Association Setup failed to establish because a mismatch occurred between the provided node ID and the configured PFCP association peer list. |
| Effect | The PFCP Association Setup procedure continues to fail while the provided node ID does not match an entry in the association peer list. |
| Recovery | Ensure there is a valid entry in the peer list configuration that matches the node ID in the PFCP association. |

3.3.10 tmnxMobGwAssocNodeIdMismatchClr

Table 27: *tmnxMobGwAssocNodeIdMismatchClr* properties

| Property name | Value |
|------------------|----------------|
| Application name | MOBILE_GATEWAY |
| Event ID | 2144 |

| Property name | Value |
|----------------------------------|--|
| Event name | tmnxMobGwAssocNodeIdMismatchClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.144 |
| Default severity | cleared |
| Source stream | main |
| Message format string | Gw - <i>\$tmnxMobGwNtfyGatewayId\$</i> , node ID match found for <i>\$tmnxMobGwPdnNtfySxAssociation\$</i> PFCP association |
| Cause | A PFCP Association Setup was re-established after the provided node ID matched a valid peer list configuration. |
| Effect | The PFCP Association Setup is established. |
| Recovery | No further action is required. |

3.3.11 tmnxMobGwAssocPfcPndIdIpTypErClr

Table 28: *tmnxMobGwAssocPfcPndIdIpTypErClr* properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2146 |
| Event name | tmnxMobGwAssocPfcPndIdIpTypErClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.146 |
| Default severity | cleared |
| Source stream | main |
| Message format string | Gw - <i>\$tmnxMobGwNtfyGatewayId\$</i> , PFCP node ID IP type match occurred after a prior mismatch for <i>\$tmnxMobGwPdnNtfySxAssociation\$</i> PFCP association |
| Cause | A PFCP Association Setup was re-established after the provided node ID IP-type value matched a valid Sx reference point peer interface address configuration. |
| Effect | The PFCP Association Setup is established. |
| Recovery | No further action is required. |

3.3.12 tmnxMobGwAssocPfcNodeIdIpTypeErr

Table 29: tmnxMobGwAssocPfcNodeIdIpTypeErr properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2145 |
| Event name | tmnxMobGwAssocPfcNodeIdIpTypeErr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.145 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw - \$tmnxMobGwNtfyGatewayId\$, pfc node ID IP type mismatched for \$tmnxMobGwPdnNtfySxAssociation\$ PFCP association |
| Cause | A PFCP Association Setup procedure failed because of a mismatch between the provided node ID IP-type value and the configured interface address types for all Sx reference point entries. |
| Effect | The PFCP Association Setup procedure continues to fail while the provided PFCP node ID IP-type continues to mismatch any address in all the Sx reference point interface configurations. |
| Recovery | Provide a valid node ID IP-type configuration in the TIMETRA-MOBILE-PDN-MIB::tmnxMobPdnPfcNodeIdIpType, or create an equivalent IP-type address interface for the Sx reference point configuration. |

3.3.13 tmnxMobGwBngChfFailAlmClr

Table 30: tmnxMobGwBngChfFailAlmClr properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2156 |
| Event name | tmnxMobGwBngChfFailAlmClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.158 |
| Default severity | major |
| Source stream | main |

| Property name | Value |
|-----------------------|---|
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , the CHF failure handling threshold alarm is cleared because upper limit of <i>\$tmnxMobGwNtfyFhAlarmLowerThr\$%</i> is reached for APN <i>\$tmnxMobGwNtfyApnName\$</i> on VM- <i>\$tmnxMobGwNtfyVmlId\$</i> |
| Cause | The lower limit of the CHF failure handling threshold was reached. |
| Effect | Enough sessions (determined by the threshold) recover from failure handling and are once again being charged as intended. |
| Recovery | Not applicable. |

3.3.14 tmnxMobGwBngChfFailAlmSet

Table 31: *tmnxMobGwBngChfFailAlmSet* properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2155 |
| Event name | tmnxMobGwBngChfFailAlmSet |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.157 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , the CHF failure handling threshold alarm is set because upper limit of <i>\$tmnxMobGwNtfyFhAlarmUpperThr\$%</i> is reached for APN <i>\$tmnxMobGwNtfyApnName\$</i> on VM- <i>\$tmnxMobGwNtfyVmlId\$</i> |
| Cause | The upper limit of the CHF failure handling threshold was reached. |
| Effect | A significant number of sessions (determined by the threshold) enter failure handling, and those sessions are not being charged as intended. |
| Recovery | Restore the CHF servers to provide full connectivity and functionality. |

3.3.15 tmnxMobGwBngPcfFailAlmClr

Table 32: tmnxMobGwBngPcfFailAlmClr properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2158 |
| Event name | tmnxMobGwBngPcfFailAlmClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.160 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , the PCF failure handling threshold alarm is cleared because upper limit of <i>\$tmnxMobGwNtfyFhAlarmLowerThr\$%</i> is reached for APN <i>\$tmnxMobGwNtfyApnName\$</i> on VM- <i>\$tmnxMobGwNtfyVmlId\$</i> |
| Cause | The lower limit of the PCF failure handling threshold was reached. |
| Effect | Enough sessions (determined by the threshold) recover from failure handling and are once again subject to PCF policy management. |
| Recovery | Not applicable. |

3.3.16 tmnxMobGwBngPcfFailAlmSet

Table 33: tmnxMobGwBngPcfFailAlmSet properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2157 |
| Event name | tmnxMobGwBngPcfFailAlmSet |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.159 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , the PCF failure handling threshold alarm is set because upper limit of <i>\$tmnxMobGwNtfyFhAlarmUpperThr\$%</i> is reached for APN <i>\$tmnxMobGwNtfyApnName\$</i> on VM- <i>\$tmnxMobGwNtfyVmlId\$</i> |

| Property name | Value |
|---------------|---|
| | $\$%$ is reached for APN $\$tmnxMobGwNtfyApnName\$$ on VM- $\$tmnxMobGwNtfyVmld\$$ |
| Cause | The upper limit of the PCF failure handling threshold was reached. |
| Effect | A significant number of sessions (determined by the threshold) enter failure handling, and those sessions are not subject to PCF policy management. |
| Recovery | Restore the PCF servers to provide full connectivity and functionality. |

3.3.17 tmnxMobGwBngUdmSdmFailAlmClr

Table 34: *tmnxMobGwBngUdmSdmFailAlmClr* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2160 |
| Event name | tmnxMobGwBngUdmSdmFailAlmClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.162 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- $\$tmnxMobGwNtfyGatewayld\$$, the UDM SDM failure handling threshold alarm is cleared because upper limit of $\$tmnxMobGwNtfyFhAlarmLowerThr\$%$ is reached for APN $\$tmnxMobGwNtfyApnName\$$ on VM- $\$tmnxMobGwNtfyVmld\$$ |
| Cause | The lower limit of the UDM failure handling threshold was reached. |
| Effect | Enough sessions (determined by the threshold) have recovered from failure handling and are once again using UDM subscription parameters. |
| Recovery | Not applicable. |

3.3.18 tmnxMobGwBngUdmSdmFailAlmSet

Table 35: tmnxMobGwBngUdmSdmFailAlmSet properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2159 |
| Event name | tmnxMobGwBngUdmSdmFailAlmSet |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.161 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , the UDM SDM failure handling threshold alarm is set because upper limit of <i>\$tmnxMobGwNtfyFhAlarmUpperThr\$%</i> is reached for APN <i>\$tmnxMobGwNtfyApnName\$</i> on VM- <i>\$tmnxMobGwNtfyVmlId\$</i> |
| Cause | The upper limit of the UDM failure handling threshold was reached. |
| Effect | A significant number of sessions (determined by the threshold) enter failure handling and are not using UDM subscription parameters. |
| Recovery | Restore the UDM servers to provide full connectivity and functionality. |

3.3.19 tmnxMobGwBngUdmUecmFailAlmClr

Table 36: tmnxMobGwBngUdmUecmFailAlmClr properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2162 |
| Event name | tmnxMobGwBngUdmUecmFailAlmClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.164 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , the UDM UECM failure handling threshold alarm is cleared because upper limit of <i>\$tmnxMobGwNtfy</i> |

| Property name | Value |
|---------------|--|
| | <i>FhAlarmLowerThr</i> % is reached for APN <i>\$tmnxMobGwNtfyApnName\$</i> on VM- <i>\$tmnxMobGwNtfyVmId\$</i> |
| Cause | The lower limit of the UDM UECM failure handling threshold was reached. |
| Effect | Enough sessions (determined by the threshold) recover from failure handling, and for those sessions, the MAG-c is registered as the serving SMF. |
| Recovery | Not applicable. |

3.3.20 tmnxMobGwBngUdmUecmFailAlmSet

Table 37: *tmnxMobGwBngUdmUecmFailAlmSet* properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2161 |
| Event name | tmnxMobGwBngUdmUecmFailAlmSet |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.163 |
| Default severity | major |
| Source stream | main |
| Message format string | <i>Gw-\$tmnxMobGwNtfyGatewayId\$</i> , the UDM UECM failure handling threshold alarm is set because upper limit of <i>\$tmnxMobGwNtfyFhAlarmUpperThr\$</i> % is reached for APN <i>\$tmnxMobGwNtfyApnName\$</i> on VM- <i>\$tmnxMobGwNtfyVmId\$</i> |
| Cause | The upper limit of the UDM UECM failure handling threshold was reached. |
| Effect | A significant number of sessions (determined by the threshold) enter failure handling, and for those sessions, the MAG-c is not registered as the serving SMF. |
| Recovery | Restore the UDM servers to provide full connectivity and functionality. |

3.3.21 tmnxMobGwCfCapacityAlarmMinor

Table 38: tmnxMobGwCfCapacityAlarmMinor properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2011 |
| Event name | tmnxMobGwCfCapacityAlarmMinor |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.7 |
| Default severity | minor |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Flash ID- <i>\$tmnxMobGwNtfyFlashId\$</i> , Flash Limit- <i>\$tmnxMobGwNtfyCfLimit\$</i> , GTP Prime Server Group- <i>\$tmnxMobGwNtfyGtpPriGrpName\$</i> . |
| Cause | The compact flash capacity reaches the 85% limit. |
| Effect | N/A |
| Recovery | N/A |

3.3.22 tmnxMobGwCfCapacityAlmMjrClear

Table 39: tmnxMobGwCfCapacityAlmMjrClear properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2014 |
| Event name | tmnxMobGwCfCapacityAlmMjrClear |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.10 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Flash ID- <i>\$tmnxMobGwNtfyFlashId\$</i> , Flash Limit- <i>\$tmnxMobGwNtfyCfLimit\$</i> , GTP Prime Server Group- <i>\$tmnxMobGwNtfyGtpPriGrpName\$</i> . |
| Cause | The compact flash capacity drops below the 90% limit. |

| Property name | Value |
|---------------|-------|
| Effect | N/A |
| Recovery | N/A |

3.3.23 tmnxMobGwCfCapacityAlmMnrClear

Table 40: tmnxMobGwCfCapacityAlmMnrClear properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2012 |
| Event name | tmnxMobGwCfCapacityAlmMnrClear |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.8 |
| Default severity | minor |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Flash ID- <i>\$tmnxMobGwNtfyFlashId\$</i> , Flash Limit- <i>\$tmnxMobGwNtfyCfLimit\$</i> , GTP Prime Server Group- <i>\$tmnxMobGwNtfyGtpPriGrpName\$</i> . |
| Cause | The compact flash capacity drops below the 80% limit. |
| Effect | N/A |
| Recovery | N/A |

3.3.24 tmnxMobGwCntrlFabricPartialFail

Table 41: tmnxMobGwCntrlFabricPartialFail properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2100 |
| Event name | tmnxMobGwCntrlFabricPartialFail |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.98 |
| Default severity | minor |
| Source stream | main |

| Property name | Value |
|-----------------------|---|
| Message format string | Detected <i>\$tmnxMobGwNtfyFailureDirection\$</i> failure for slot <i>\$tmnxMobGwNtfySlot\$</i> on control fabric <i>\$tmnxMobGwNtfyFabricId\$</i> |
| Cause | A <i>tmnxMobGwCntrlFabricPartialFail</i> is generated when a card loses connectivity to other cards in a particular direction over a particular control fabric. The card ID is indicated in <i>tmnxMobGwNtfySlot</i> , the failed fabric ID is indicated in <i>tmnxMobGwNtfyFabricId</i> and the direction of the failure (transmit/receive) is indicated in <i>tmnxMobGwNtfyFailureDirection</i> . |
| Effect | The system uses a different operational control fabric to communicate with the affected card. |
| Recovery | Manual intervention may be required to restore the connectivity. |

3.3.25 tmnxMobGwControlFabricFailure

Table 42: *tmnxMobGwControlFabricFailure* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2101 |
| Event name | tmnxMobGwControlFabricFailure |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.99 |
| Default severity | minor |
| Source stream | main |
| Message format string | Detected <i>\$tmnxMobGwNtfyFailureDirection\$</i> failure for slot <i>\$tmnxMobGwNtfySlot\$</i> on all control fabrics |
| Cause | A loss of connectivity to other cards occurred in a particular direction over all available control fabrics. |
| Effect | The card cannot function properly as part of the system. |
| Recovery | Attempt to restore connectivity by rebooting the affected card. |

3.3.26 tmnxMobGwDdnThrottlingStart

Table 43: tmnxMobGwDdnThrottlingStart properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2033 |
| Event name | tmnxMobGwDdnThrottlingStart |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.29 |
| Default severity | warning |
| Source stream | main |
| Message format string | Acct Application: Throttling DDN: Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Ref point- <i>\$tmnxMobGwNtfyRefPointType\$</i> , Ref protocol- <i>\$tmnxMobGwNtfyRefPointProtocol\$</i> , RefPointName- <i>\$tmnxMobGwNtfyRefPointName\$</i> , address type- <i>\$tmnxMobGwNtfyRfPtPeerAddrType\$</i> , peer address- <i>\$tmnxMobGwNtfyRfPtPeerAddr\$</i> , port- <i>\$tmnxMobGwNtfyRfPtPeerPort\$</i> , duration- <i>\$tmnxMobGwNtfyDdnThrotDuration\$</i> , factor- <i>\$tmnxMobGwNtfyDdnThrotFactor\$</i> |
| Cause | The SGW starts throttling the DDN when it receives a throttling instruction carried in the "downlink (DL) low priority traffic Throttling" IE from a peer node. |
| Effect | The SGW starts throttling the DDN based on a priority threshold value. The traffic with a priority value higher than or equal to the threshold value is considered as a bearer for non-priority traffic. |
| Recovery | When the throttling time is over, the SGW stops throttling the DDN. |

3.3.27 tmnxMobGwDdnThrottlingStop

Table 44: tmnxMobGwDdnThrottlingStop properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2034 |
| Event name | tmnxMobGwDdnThrottlingStop |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.30 |
| Default severity | warning |

| Property name | Value |
|-----------------------|--|
| Source stream | main |
| Message format string | Acct Application: Throttling DDN: Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Ref point- <i>\$tmnxMobGwNtfyRefPointType\$</i> , Ref protocol- <i>\$tmnxMobGwNtfyRefPointProtocol\$</i> , RefPointName- <i>\$tmnxMobGwNtfyRefPointName\$</i> , address type- <i>\$tmnxMobGwNtfyRfPtPeerAddrType\$</i> , peer address- <i>\$tmnxMobGwNtfyRfPtPeerAddr\$</i> , port- <i>\$tmnxMobGwNtfyRfPtPeerPort\$</i> , duration- <i>\$tmnxMobGwNtfyDdnThrotDuration\$</i> , factor- <i>\$tmnxMobGwNtfyDdnThrotFactor\$</i> |
| Cause | The SGW stops throttling the DDN when the throttling time is over. |
| Effect | The SGW stops throttling the DDN based on a priority threshold value. All DDNs are sent to the peer node. |
| Recovery | When another throttling instruction is received from a peer node, the SGW starts throttling the DDN. |

3.3.28 tmnxMobGwDnsSnpFqdnIpLimitAlarm

Table 45: *tmnxMobGwDnsSnpFqdnIpLimitAlarm* properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2102 |
| Event name | tmnxMobGwDnsSnpFqdnIpLimitAlarm |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.100 |
| Default severity | minor |
| Source stream | main |
| Message format string | Gw: <i>\$tmnxMobGwNtfyGatewayId\$</i> Number of server addresses learned by DNS Snooping reached <i>\$tmnxMobGwDnsSnpFqdnThres\$</i> % of maximum <i>\$tmnxMobGwDnsSnpFqdnIpMax\$</i> |
| Cause | The number of stored DNS-resolved IP addresses approaches a threshold limit of the maximum number of cacheable addresses. The threshold is indicated by tmnxMobGwDnsSnpFqdnThres as a percentage, and the maximum size of stored IP addresses is indicated by the tmnxMobGwDnsSnpFqdnIpMax value. |
| Effect | The PGW may reach the maximum limit and may not be able to store new IP addresses. |
| Recovery | Clear the resolved filters for the specified FQDN list. |

3.3.29 tmnxMobGwLciOverload

Table 46: tmnxMobGwLciOverload properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2080 |
| Event name | tmnxMobGwLciOverload |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.78 |
| Default severity | minor |
| Source stream | main |
| Message format string | Mobile Gateway in GTP-C LCI 100% |
| Cause | The resources for the mobile gateway group reached their limit. |
| Effect | The mobile gateway group resources are at critical levels. The system attempts to lower resource usage for this mobile gateway group. |
| Recovery | None |

3.3.30 tmnxMobGwLciOverloadClear

Table 47: tmnxMobGwLciOverloadClear properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2081 |
| Event name | tmnxMobGwLciOverloadClear |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.79 |
| Default severity | minor |
| Source stream | main |
| Message format string | Mobile Gateway GTP-C no longer at LCI 100% |
| Cause | The resources for the mobile gateway group are back to normal operating levels. |
| Effect | The mobile gateway group is back to normal operating levels. |

| Property name | Value |
|---------------|--|
| Recovery | None, the system is back to the normal operating levels. |

3.3.31 tmnxMobGwMcRedPurgeRebootStandby

Table 48: tmnxMobGwMcRedPurgeRebootStandby properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2063 |
| Event name | tmnxMobGwMcRedPurgeRebootStandby |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.61 |
| Default severity | minor |
| Source stream | main |
| Message format string | MC_RED purge: Active card- <i>\$tmnxMobGwNtfyActiveCardSlotNum\$</i> initialized reboot on standby card- <i>\$tmnxMobGwNtfyStandbyCardSlotNum\$</i> |
| Cause | In the case of a multi-chassis redundancy purge, if the RED state is not 'hot', the active card initializes a reboot on the standby card after the purge finishes on the active card. |
| Effect | The standby card reboots. |
| Recovery | No further action is required. |

3.3.32 tmnxMobGwNnrfBlocklistAlarm

Table 49: tmnxMobGwNnrfBlocklistAlarm properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2126 |
| Event name | tmnxMobGwNnrfBlocklistAlarm |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.126 |
| Default severity | warning |

| Property name | Value |
|-----------------------|--|
| Source stream | main |
| Message format string | NRF peer for service <i>\$tmnxMobGwNtfyNrfServiceType\$</i> on GW- <i>\$tmnxMobGwNtfyGatewayId\$</i> is block-listed |
| Cause | All the NRF peers for the nrf-nfm or nrf-disc service are block-listed after failure responses or response timeouts. |
| Effect | The block-list duration is not applied. All NRF peers are sending failure responses or the responses time out. The gateway continuously retries service requests to all peers. |
| Recovery | The alarm is cleared when the first NRF peer from the block list is successfully contacted (a success HTTP status is received). |

3.3.33 tmnxMobGwNrfBlocklistAlarmClear

Table 50: *tmnxMobGwNrfBlocklistAlarmClear* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2127 |
| Event name | tmnxMobGwNrfBlocklistAlarmClear |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.127 |
| Default severity | warning |
| Source stream | main |
| Message format string | NRF peer for service <i>\$tmnxMobGwNtfyNrfServiceType\$</i> on GW- <i>\$tmnxMobGwNtfyGatewayId\$</i> is no longer block-listed |
| Cause | All the NRF peers for the nrf-nfm or nrf-disc service are no longer block-listed. |
| Effect | The block-list duration is applied. |
| Recovery | No further action required. |

3.3.34 tmnxMobGwNrfHeartbeatAlarm

Table 51: tmnxMobGwNrfHeartbeatAlarm properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2094 |
| Event name | tmnxMobGwNrfHeartbeatAlarm |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.90 |
| Default severity | major |
| Source stream | main |
| Message format string | NRF heartbeat failed for peer <i>\$tmnxMobGwNrfPtPeerAddr\$</i> on GW <i>\$tmnxMobGwNrfGatewayId\$</i> with error: <i>\$tmnxMobGwNrfHbAlarmReason\$</i> |
| Cause | Loss of connectivity to the NRF (NRF failure). |
| Effect | The NRF does not consider the MAG-c SMF or UPF to be registered and eligible for discovery anymore. The NRF may also consider the MAG-c SMF or UPF to be out of service and may notify the subscribed peer NF instances. |
| Recovery | Recovery is determined according to the failure handling of the failed HB responses, and failover to the next NRF is concluded. |

3.3.35 tmnxMobGwNrfHeartbeatAlarmClear

Table 52: tmnxMobGwNrfHeartbeatAlarmClear properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2095 |
| Event name | tmnxMobGwNrfHeartbeatAlarmClear |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.91 |
| Default severity | major |
| Source stream | main |

| Property name | Value |
|-----------------------|--|
| Message format string | NRF heartbeat succeeded for peer <i>\$tmnxMobGwNtfyRfPtPeerAddr\$</i> on GW <i>\$tmnxMobGwNtfyGatewayId\$</i> with error: <i>\$tmnxMobGwNtfyNrfHbAlarmReason\$</i> |
| Cause | Successful Heartbeat message request/response sequence with the NRF. |
| Effect | The NRF considers the MAG-c SMF or UPF to be registered and eligible for discovery. |
| Recovery | No further action is required. |

3.3.36 tmnxMobGwOciOverload

Table 53: *tmnxMobGwOciOverload* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2082 |
| Event name | tmnxMobGwOciOverload |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.80 |
| Default severity | major |
| Source stream | main |
| Message format string | Mobile Gateway in GTP-C OCI overload |
| Cause | The resources for the mobile gateway group were almost exhausted because of high load. |
| Effect | The mobile gateway group resources are at critical levels. The system attempts to lower resource usage on this mobile gateway group. |
| Recovery | None. |

3.3.37 tmnxMobGwOciOverloadClear

Table 54: *tmnxMobGwOciOverloadClear* properties

| Property name | Value |
|------------------|----------------|
| Application name | MOBILE_GATEWAY |

| Property name | Value |
|----------------------------------|---|
| Event ID | 2083 |
| Event name | tmnxMobGwOciOverloadClear |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.81 |
| Default severity | major |
| Source stream | main |
| Message format string | Mobile Gateway no longer in GTP-C overload |
| Cause | The resources for the mobile gateway group returned to normal operating levels. |
| Effect | The mobile gateway group returns to normal operating levels. |
| Recovery | None, the system is back to the normal operating levels. |

3.3.38 tmnxMobGwOciOvldThrtStart

Table 55: tmnxMobGwOciOvldThrtStart properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2103 |
| Event name | tmnxMobGwOciOvldThrtStart |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.101 |
| Default severity | major |
| Source stream | main |
| Message format string | The mobile gateway has started throttling incoming call flows due to local overload. |
| Cause | The resources for the mobile gateway group were almost exhausted because of high load. |
| Effect | The mobile gateway group resources are at a critical level. The system attempts to lower the resource usage on this mobile gateway group. |
| Recovery | The mobile-gateway stops throttling incoming call flows when it is out of local overload. |

3.3.39 tmnxMobGwOciOvldThrtStop

Table 56: tmnxMobGwOciOvldThrtStop properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2104 |
| Event name | tmnxMobGwOciOvldThrtStop |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.102 |
| Default severity | major |
| Source stream | main |
| Message format string | The mobile gateway has stopped throttling incoming call flows due to local overload. |
| Cause | Incoming call flows have not been received for the last 30 seconds or the resources for the mobile gateway group have returned to normal operating levels for the last 30 seconds. |
| Effect | The mobile gateway is no longer throttling incoming call flows because of local overload. |
| Recovery | Not applicable. |

3.3.40 tmnxMobGwPathMgmtPeerState

Table 57: tmnxMobGwPathMgmtPeerState properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2001 |
| Event name | tmnxMobGwPathMgmtPeerState |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.1 |
| Default severity | major |
| Source stream | main |
| Message format string | Path Management: Peer State: \$tmnxMobGwNtfyPathMgmtPeerState\$: Gw-\$tmnxMobGwNtfyGatewayId\$, Ref point-\$tmnxMobGwNtfyRefPointType\$, protocol- \$tmnxMobGwNtfyRefPointProtocol\$, RefPoint Name-\$tmnxMobGwNtfyRefPointName\$,peer-\$tmnxMobGwNtfyRfPt |

| Property name | Value |
|---------------|--|
| | <i>PeerAddr</i> \$, port- <i>\$tmnxMobGwNtfyRfPtPeerPort</i> \$, Local address - <i>\$tmnxMobGwNtfyPathLocAddress</i> \$, Previous Restart Counter- <i>\$tmnxMobGwNtfyPrevRestartCounter</i> \$, Current Restart Counter- <i>\$tmnxMobGwNtfyCurrRestartCounter</i> \$, Peer Restart Reason- <i>\$tmnxMobGwNtfyPeerRestartReason</i> \$, Pkt Seq Number- <i>\$tmnxMobGwNtfyPeerRestPktSeqNum</i> \$, Peer Type- <i>\$tmnxMobGwNtfySigPeerType</i> \$, Plane Type- <i>\$tmnxMobGwNtfySigPlaneType</i> \$. |
| Cause | There has been a change in the reference point peer state during path management. The supported trap event values are the following: Added - raised when a new peer is identified by incoming messages GUp - raised when a peer moves to the UP state, for an SGW peer, this state change happens when a CS Req is received. for PGW peers, this state change happens when a CS Resp from the PGW peer is received (this is to make sure that Path UP trap is generated only for a real PGW peer in case of GTP-C redirection) Down - raised when a peer moves to the FAULT state while detecting a path management failure. Idle - raised when a peer moves to the IDLE state after a session cleanup is done because of a path management Failure, Detach or Admin delete. Restart - raised when a peer restart is detected. It is associated with the Peer RESTART state. Deleted - raised when a peer entry is deleted because of a peer aging out. A peer ages out when it is Idle for more than the Age Out Interval. |
| Effect | N/A |
| Recovery | N/A |

3.3.41 tmnxMobGwPcmdOperStateChange

Table 58: *tmnxMobGwPcmdOperStateChange* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2045 |
| Event name | tmnxMobGwPcmdOperStateChange |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.43 |
| Default severity | minor |
| Source stream | main |
| Message format string | PCMD: Oper State: <i>\$tmnxMobGwNtfyPcmdOperState</i> \$. Gw- <i>\$tmnxMobGwNtfyGatewayId</i> \$, PCMD profile- <i>\$tmnxMobGwNtfyPcmdProfile</i> \$ |

| Property name | Value |
|---------------|---|
| Cause | The PCMD operational state changes when the destination address reachability changes. |
| Effect | When the PCMD state is down, the generated PCMD packets are not sent to the destination address. When the PCMD state is up, the PCMD packets are sent to the destination address. |
| Recovery | If the PCMD state is down, the generated PCMD packets are dropped. |

3.3.42 tmnxMobGwPfcRestoreInProg

Table 59: tmnxMobGwPfcRestoreInProg properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2122 |
| Event name | tmnxMobGwPfcRestoreInProg |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.122 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw-\$tmnxMobGwNtfyGatewayId\$ VRtr- \$tmnxMobGwNtfyVrtrId\$ Ref PointType-\$tmnxMobGwNtfyRefPointType\$ RefPointName-\$tmnxMobGwNtfyRefPointName\$ PFCP restoration in progress for RemotePeer Address- \$tmnxMobGwNtfyRfPtPeerAddr\$ LocalPeerAddress-\$tmnxMobGwNtfyPeerLocAddress\$ RestoreTimer-\$tmnxMobGwNtfyRestoreTimer\$ Nodeld- \$tmnxMobGwNtfyPeerNodeld\$ |
| Cause | A PFCP keepalive failure between UP and CP has been detected. |
| Effect | The restoration timer starts. |
| Recovery | Restore the path between the UP and the CP to allow keepalives to succeed again. If keepalives recover before the restoration timer times out, the CP and the UP perform an audit and recover from the failure automatically. |

3.3.43 tmnxMobGwPfcViaUpFuncFailureClr

Table 60: tmnxMobGwPfcViaUpFuncFailureClr properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2129 |
| Event name | tmnxMobGwPfcViaUpFuncFailureClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.129 |
| Default severity | cleared |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , <i>\$tmnxMobGwNtfyGrpName\$</i> detected a PFCP-u tunnel connectivity re-established between the CP function and UP function. |
| Cause | The PFCP-u tunnel used for via-up-function (radius-group or dhcp-server-group) traffic between the CP and the UP function is failing to be re-established. |
| Effect | Any traffic routed over the PFCP-u tunnel will no longer fail. |
| Recovery | No further action required. |

3.3.44 tmnxMobGwRadGrpFailAlarm

Table 61: tmnxMobGwRadGrpFailAlarm properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2024 |
| Event name | tmnxMobGwRadGrpFailAlarm |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.20 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Radius Server Group- <i>\$tmnxMobGwNtfyRadGrpName\$</i> , Group State- <i>\$tmnxMobGwNtfyRadGrpState\$</i> . |

| Property name | Value |
|---------------|--|
| Cause | All the RADIUS servers for the group are in a down state. |
| Effect | When the group of RADIUS servers fails, RADIUS messages may not be sent to the group. |
| Recovery | The RADIUS server group recovers from this failure mode when one of its servers returns to the up state. |

3.3.45 tmnxMobGwRadGrpFailAlarmClrd

Table 62: tmnxMobGwRadGrpFailAlarmClrd properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2025 |
| Event name | tmnxMobGwRadGrpFailAlarmClrd |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.21 |
| Default severity | minor |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Radius Server Group- <i>\$tmnxMobGwNtfyRadGrpName\$</i> , Group State- <i>\$tmnxMobGwNtfyRadGrpState\$</i> . |
| Cause | The RADIUS server group recovered from the previous failure mode and at least one of its servers has transitioned to the up state. |
| Effect | The operation for the RADIUS group returns to normal. |
| Recovery | No further action is required. |

3.3.46 tmnxMobGwRadPeerFailAlarm

Table 63: tmnxMobGwRadPeerFailAlarm properties

| Property name | Value |
|------------------|---------------------------|
| Application name | MOBILE_GATEWAY |
| Event ID | 2022 |
| Event name | tmnxMobGwRadPeerFailAlarm |

| Property name | Value |
|----------------------------------|---|
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.18 |
| Default severity | minor |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Radius Server Group- <i>\$tmnxMobGwNtfyRadGrpName\$</i> , Address- <i>\$tmnxMobGwNtfyRadPeerAddr\$</i> , Authentication port- <i>\$tmnxMobGwNtfyRadPeerAuthPort\$</i> , Accounting port- <i>\$tmnxMobGwNtfyRadPeerAcctPort\$</i> , Peer State- <i>\$tmnxMobGwNtfyRadPeerState\$</i> . |
| Cause | The state for the RADIUS server changed to down. |
| Effect | RADIUS messages may not be sent to the RADIUS server. |
| Recovery | RADIUS messages can continue to be sent to a RADIUS server after the RADIUS server's state changes back to up or the dead timer expires. |

3.3.47 tmnxMobGwRadPeerFailAlarmClrd

Table 64: *tmnxMobGwRadPeerFailAlarmClrd* properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2023 |
| Event name | tmnxMobGwRadPeerFailAlarmClrd |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.19 |
| Default severity | minor |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Radius Server Group- <i>\$tmnxMobGwNtfyRadGrpName\$</i> , Address- <i>\$tmnxMobGwNtfyRadPeerAddr\$</i> , Authentication port- <i>\$tmnxMobGwNtfyRadPeerAuthPort\$</i> , Accounting port- <i>\$tmnxMobGwNtfyRadPeerAcctPort\$</i> , Peer State- <i>\$tmnxMobGwNtfyRadPeerState\$</i> . |
| Cause | The RADIUS server recovered from the previous failure mode, and one of its servers has transitioned to the up state. |
| Effect | The operation for the RADIUS server returns to normal. |
| Recovery | No further action is required. |

3.3.48 tmnxMobGwSbiPeerState

Table 65: tmnxMobGwSbiPeerState properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2130 |
| Event name | tmnxMobGwSbiPeerState |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.130 |
| Default severity | warning |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , Group ID- <i>\$tmnxMobGwNtfySbiGroupId\$</i> , NF service name- <i>\$tmnxMobGwNtfySbiNfServiceName\$</i> , Service Instance- <i>\$tmnxMobGwNtfySbiNfServiceIns\$</i> , peer UUID- <i>\$tmnxMobGwNtfySbiPeerUuid\$</i> , peer ip address- <i>\$tmnxMobGwNtfySbiPeerIpAddress\$</i> , peer port- <i>\$tmnxMobGwNtfySbiPeerPort\$</i> , connection state- <i>\$tmnxMobGwNtfySbiConnectionState\$</i> , NF service state- <i>\$tmnxMobGwNtfySbiNfServiceState\$</i> . |
| Cause | A change occurred in the NF peer connection status or a peer was deleted from the peer list. |
| Effect | N/A. |
| Recovery | N/A. |

3.3.49 tmnxMobPdnApnMaxPdnConnAlarm

Table 66: tmnxMobPdnApnMaxPdnConnAlarm properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2035 |
| Event name | tmnxMobPdnApnMaxPdnConnAlarm |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.33 |
| Default severity | major |
| Source stream | main |

| Property name | Value |
|-----------------------|---|
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , APN Name- <i>\$tmnxMobGwNtfyApnName\$</i> . |
| Cause | The maximum number of PDN connections for this APN on the gateway was reached. |
| Effect | New PDN connections are not accepted until the limit drops below the value of TIMETRA-MOBILE-PDN-MIB::tmnxMobPdnApnMaxPdnConnections. |
| Recovery | To accept new PDN connections, the system has to wait until the maximum PDN connections number drops below the threshold. |

3.3.50 tmnxMobPdnApnMaxPdnConnAlarmClr

Table 67: tmnxMobPdnApnMaxPdnConnAlarmClr properties

| Property name | Value |
|----------------------------------|---|
| Application name | MOBILE_GATEWAY |
| Event ID | 2036 |
| Event name | tmnxMobPdnApnMaxPdnConnAlarmClr |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.34 |
| Default severity | major |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , APN Name- <i>\$tmnxMobGwNtfyApnName\$</i> . |
| Cause | The existing number of PDN connections for this APN on the gateway drops below the value of TIMETRA-MOBILE-PDN-MIB::tmnxMobPdnApnMaxPdnConnections. |
| Effect | New PDN connections are accepted. |
| Recovery | No further action is required. |

3.3.51 tmnxMobPdnBearerContextClear

Table 68: tmnxMobPdnBearerContextClear properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2153 |
| Event name | tmnxMobPdnBearerContextClear |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.155 |
| Default severity | warning |
| Source stream | main |
| Message format string | Clear bearer context in PDN \$tmnxMobGwNtfyGatewayId\$ \$tmnxMobGwNtfyLongText\$ \$tmnxMobGwNtfyStartEnd\$ (#\$tmnxMobGwNtfyNumber\$) |
| Cause | The system started or terminated the processing a request to clear a PDN bearer context. The request can be made with the clear mobile-gateway pdn bearer-context CLI command or one of the appropriate rows in the TIMETRA-CLEAR-MIB::tmnxClearTable, for example the 'clearMobPdnBearerContext' row. |
| Effect | In the time interval between the start and end notification, the system clears a number of PDN bearer contexts that match the specified parameters. The UEs associated with the bearer contexts lose their connection with the PDN. |
| Recovery | None. |

3.3.52 tmnxMobPdnLaaPfxInsufficientMem

Table 69: tmnxMobPdnLaaPfxInsufficientMem properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2113 |
| Event name | tmnxMobPdnLaaPfxInsufficientMem |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.113 |
| Default severity | warning |

| Property name | Value |
|-----------------------|---|
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , network realm <i>\$tmnxMobGwNtfyNwRealmName\$</i> , pool <i>\$tmnxMobGwNtfyPoolName\$</i> , prefix <i>\$tmnxMobGwNtfyAddr\$/\$tmnxMobGwNtfyPfxLength\$</i> not operational due to insufficient memory |
| Cause | There is insufficient memory for an IP address prefix and all of its micronets. |
| Effect | The IP address prefix is not activated, and its operational state goes down. |
| Recovery | Add memory to the system, or reduce the number of the prefix micronets. |

3.3.53 tmnxMobPdnLaaPINoFreeMnets

Table 70: *tmnxMobPdnLaaPINoFreeMnets* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2136 |
| Event name | tmnxMobPdnLaaPINoFreeMnets |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.136 |
| Default severity | minor |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , network realm <i>\$tmnxMobGwNtfyNwRealmName\$</i> , pool <i>\$tmnxMobGwNtfyPoolName\$</i> IPv6 type <i>\$tmnxMobGwNtfyIpv6AssignmentType\$</i> : no more free <i>\$tmnxMobGwNtfyLaaUnfragmentedMn\$</i> micronets <i>\$tmnxMobGwNtfyTruthValue\$</i> |
| Cause | The last available micronet of its kind in the pool is activated. |
| Effect | Setup of new end user sessions starts to fail. |
| Recovery | Add prefixes to the pool. |

3.3.54 tmnxMobPdnLaaPINumFreeMnetsLow

Table 71: tmnxMobPdnLaaPINumFreeMnetsLow properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2110 |
| Event name | tmnxMobPdnLaaPINumFreeMnetsLow |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.108 |
| Default severity | warning |
| Source stream | main |
| Message format string | Gw- <i>\$tmnxMobGwNtfyGatewayId\$</i> , network realm <i>\$tmnxMobGwNtfyNwRealmName\$</i> , pool <i>\$tmnxMobGwNtfyPoolName\$</i> IPv6 type <i>\$tmnxMobGwNtfyIpv6AssignmentType\$</i> : running low on <i>\$tmnxMobGwNtfyLaaUnfragmentedMn\$</i> micronets <i>\$tmnxMobGwNtfyTruthValue\$</i> |
| Cause | A micronet is activated while the number of free micronets in the pool is already low. |
| Effect | None. |
| Recovery | No recovery is immediately required. However, it is recommended to add prefixes to avoid complete depletion of the pool. |

3.3.55 tmnxMobProfNodeSelTrgtSugstRebal

Table 72: tmnxMobProfNodeSelTrgtSugstRebal properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2149 |
| Event name | tmnxMobProfNodeSelTrgtSugstRebal |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.151 |
| Default severity | warning |
| Source stream | main |

| Property name | Value |
|-----------------------|--|
| Message format string | Evaluate target-profile <i>\$tmnxMobGwNtfyProfileName\$</i> and rebalance if necessary - new UP= <i>\$tmnxMobGwNtfyUpPeerAddress\$</i> , surviving number of UPs= <i>\$tmnxMobGwNtfyNumber\$</i> |
| Cause | The system reconnected to a UPF after having been disconnected. |
| Effect | While the UPF connection was down session distribution among the UPFs in a target profile may have become unbalanced. This event indicates session load rebalancing may be necessary. |
| Recovery | Evaluate session load among the available UPFs in the target profile, and if necessary, rebalance using a clear operation. |

3.3.56 tmnxMobProfNodeSelTrgtSugstRevrt

Table 73: *tmnxMobProfNodeSelTrgtSugstRevrt* properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2150 |
| Event name | tmnxMobProfNodeSelTrgtSugstRevrt |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.152 |
| Default severity | warning |
| Source stream | main |
| Message format string | Evaluate target-profile <i>\$tmnxMobGwNtfyProfileName\$</i> and revert if necessary |
| Cause | The number of available UPFs in a target profile entry reached the necessary minimum threshold. |
| Effect | While the number of available UPF connections was below the minimum threshold new sessions are directed to backup UPFs. This event indicates it may be appropriate to revert sessions to primary UPFs. |
| Recovery | Session load among primary and secondary UPFs of the target profile should be evaluated and if necessary, reverted using a clear operation. |

3.3.57 tmnxOverlayFabricFailure

Table 74: tmnxOverlayFabricFailure properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2072 |
| Event name | tmnxOverlayFabricFailure |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.70 |
| Default severity | minor |
| Source stream | main |
| Message format string | Detected <i>\$tmnxMobGwNtfyFailureDirection\$</i> failure for slot <i>\$tmnxMobGwNtfySlot\$</i> on all overlay fabrics |
| Cause | A loss of connectivity occurred to other cards in a particular direction over all available overlay fabrics. |
| Effect | The card cannot function properly as part of the system. |
| Recovery | Attempt to restore connectivity by rebooting the affected card. |

3.3.58 tmnxOverlayFabricPartialFailure

Table 75: tmnxOverlayFabricPartialFailure properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2073 |
| Event name | tmnxOverlayFabricPartialFailure |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.71 |
| Default severity | minor |
| Source stream | main |
| Message format string | Detected <i>\$tmnxMobGwNtfyFailureDirection\$</i> failure for slot <i>\$tmnxMobGwNtfySlot\$</i> on overlay fabric <i>\$tmnxMobGwNtfyFabricId\$</i> |
| Cause | Loss of connectivity between the affected card and the other cards in a particular direction over a particular overlay fabric. |

| Property name | Value |
|---------------|--|
| Effect | The system uses a different operational overlay fabric to communicate with the affected card, but the capacity is reduced. |
| Recovery | Manual intervention may be required to restore the connectivity. |

3.3.59 tmnxOverlayFabricStatus

Table 76: tmnxOverlayFabricStatus properties

| Property name | Value |
|----------------------------------|--|
| Application name | MOBILE_GATEWAY |
| Event ID | 2060 |
| Event name | tmnxOverlayFabricStatus |
| SNMP notification prefix and OID | TIMETRA-MOBILE-GATEWAY-MIB.tmnxMobGatewayNotifications.58 |
| Default severity | major |
| Source stream | main |
| Message format string | Operational state of last overlay fabric port transitioned to <i>\$tmnxMobGwNtfyOverlayFabricState\$</i> state for VM <i>\$tmnxMobGwNtfyVmId\$</i> |
| Cause | A change occurred in the operational state of the overlay fabric switch, either when the last operational overlay fabric port transitioned to the down state or the first overlay fabric port transitioned to an up state. |
| Effect | If the value of tmnxMobGwNtfyOverlayFabricState is down, the VM fails (crashes) and ceases to process any new packets. |
| Recovery | If the value of tmnxMobGwNtfyOverlayFabricState is down, the VM fails to process new packets and reboots. The VM remains in the booting state until the value of tmnxMobGwNtfyOverlayFabricState changes to up. |

Customer document and product support



Customer documentation

[Customer documentation welcome page](#)



Technical support

[Product support portal](#)



Documentation feedback

[Customer documentation feedback](#)