Nokia Service Router Linux
7215 Interconnect System
7220 Interconnect Router
7250 Interconnect Router

Release 26.10

CLI Plug-in Guide

3HE 22250 AAAC TQZZA
Edition: 01
November 2026

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Nokia is committed to diversity and inclusion. We are continuously reviewing our customer documentation and consulting with standards bodies to ensure that terminology is inclusive and aligned with the industry. Our future customer documentation will be updated accordingly.

This document includes Nokia proprietary and confidential information, which may not be distributed or disclosed to any third parties without the prior written consent of Nokia.

This document is intended for use by Nokia's customers ("You"/"Your") in connection with a product purchased or licensed from any company within Nokia Group of Companies. Use this document as agreed. You agree to notify Nokia of any errors you may find in this document; however, should you elect to use this document for any purpose(s) for which it is not intended, You understand and warrant that any determinations You may make or actions You may take will be based upon Your independent judgment and analysis of the content of this document.

Nokia reserves the right to make changes to this document without notice. At all times, the controlling version is the one available on Nokia's site.

No part of this document may be modified.

NO WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY WARRANTY OF AVAILABILITY, ACCURACY, RELIABILITY, TITLE, NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE, IS MADE IN RELATION TO THE CONTENT OF THIS DOCUMENT. IN NO EVENT WILL NOKIA BE LIABLE FOR ANY DAMAGES, INCLUDING BUT NOT LIMITED TO SPECIAL, DIRECT, INDIRECT, INCIDENTAL OR CONSEQUENTIAL OR ANY LOSSES, SUCH AS BUT NOT LIMITED TO LOSS OF PROFIT, REVENUE, BUSINESS INTERRUPTION, BUSINESS OPPORTUNITY OR DATA THAT MAY ARISE FROM THE USE OF THIS DOCUMENT OR THE INFORMATION IN IT, EVEN IN THE CASE OF ERRORS IN OR OMISSIONS FROM THIS DOCUMENT OR ITS CONTENT.

Copyright and trademark: Nokia is a registered trademark of Nokia Corporation. Other product names mentioned in this document may be trademarks of their respective owners.

The registered trademark Linux® is used pursuant to a sublicense from the Linux Foundation, the exclusive licensee of Linus Torvalds, owner of the mark on a worldwide basis.

© 2026 Nokia.

Table of contents

1 About this guide 5
1.1 Precautionary and information messages 5
1.2 Conventions 5

2 What's new 7

3 Show routines 8
3.1 Creating a show routine 8
3.1.1 Building the SchemaNode 9
3.1.2 Retrieving the state from the management server 10
3.1.3 Populating a data object 10
3.1.4 Adding formatter instances 11
3.1.5 Implementing the callback method 11
3.1.6 Show routine code example 12
3.1.7 Using streaming to optimize reports 13

4 Managing CLI plug-ins 16
4.1 Installing a CLI plug-in 16
4.2 Modifying a CLI plug-in 16
4.3 Removing a CLI plug-in 17

5 Classes and utility functions 18
5.1 Formatters 18
5.1.1 ColumnFormatter 19
5.1.2 TagValueFormatter 20
5.1.3 TagValueWithKeyLineFormatter 21
5.1.4 Indent 21
5.1.5 Border 21
5.1.6 Header 22
5.1.7 Footer 23
5.1.8 Whiteline 23
5.1.9 FilteredFormatter 24
5.2 Format utilities 25
5.2.1 ColumnPrinter 25

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

5.2.2 TagValuePrinter 26
5.2.3 TagValueWithKeyLinePrinter 27
5.2.4 print_line 27
5.2.5 print_double_line 28
5.2.6 indent 28
5.2.7 format_value 28
5.3 Data 28
5.4 DataChildrenOfType 31
5.5 SchemaNode 33

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

1 About this guide

The Nokia Service Router Linux (SR Linux) CLI is a python-based application that can load dynamic plug-ins. Plug-ins are custom show commands that you can create and run from the SR Linux CLI. This document describes how to create custom CLI plug-ins, and defines the classes and utility functions used to create them. It also defines how to install, modify, and remove a CLI plug-in.

This document is intended for network technicians, administrators, operators, service providers, and others who need to create, install, and use custom show commands.

Note:
This manual covers the current release and may also contain some content to be released in later maintenance loads. See the *SR Linux Software Release Notes* for information about features supported in each load.

Configuration and command outputs shown in this guide are examples only; actual displays may differ depending on supported functionality and user configuration.

1.1 Precautionary and information messages

The following are information symbols used in the documentation.

DANGER: Danger warns that the described activity or situation may result in serious personal injury or death. An electric shock hazard could exist. Before you begin work on this equipment, be aware of hazards involving electrical circuitry, be familiar with networking environments, and implement accident prevention procedures.

WARNING: Warning indicates that the described activity or situation may, or will, cause equipment damage, serious performance problems, or loss of data.

Caution: Caution indicates that the described activity or situation may reduce your component or system performance.

Note: Note provides additional operational information.

Tip: Tip provides suggestions for use or best practices.

1.2 Conventions

The Nokia SR Linux documentation uses the following command conventions:

- **Bold** type indicates a command that the user must enter.
- Input and output examples are displayed in `Courier` text.
- A vertical bar (|) indicates a mutually exclusive argument.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

- Square brackets ([ ]) indicate optional elements.
- Braces ({ }) indicate a required choice. When braces are contained within square brackets, they indicate a required choice within an optional element.
- *Italic* type indicates a variable.

The following table outlines platform grouping conventions used in the SR Linux documentation suite.

Note: Some platforms in the 7250 IXR support mixed systems. For more information about mixed system support, see "Chassis types" in the *Configuration Basics Guide*.

Table 1: Platform grouping legend

Platform group	Description
7215 IXS	7215 IXS-A1[1]
7220 IXR	All 7220 IXR platforms
7220 IXR-D*x*	7220 IXR-D1, 7220 IXR-D2, 7220 IXR-D2L, 7220 IXR-D3, 7220 IXR-D3L, 7220 IXR-D4, 7220 IXR-D5
7220 IXR-H*x*	7220 IXR-H2, 7220 IXR-H3, 7220 IXR-H4, 7220 IXR-H4-32D, 7220 IXR-H5-32D, 7220 IXR-H5-64D, 7220 IXR-H5-64O, 7220 IXR-H5-64O-512, 7220 IXR-H6-64
7250 IXR[2]	7250 IXR platforms
7250 IXR Gen 2	7250 IXR-6, 7250 IXR-10
7250 IXR Gen 2c+	7250 IXR-6e with IMM2, 7250 IXR-10e with IMM2, 7250 IXR-X1b, 7250 IXR-X3b
7250 IXR Gen 3	7250 IXR-6e with IMM3, 7250 IXR-10e with IMM3, 7250 IXR-18e, 7250 IXR-X4, 7250 IXR-X4 OSFP
7250 IXR-6e/10e (mixed system)	7250 IXR-6e (mixed system)[3], 7250 IXR-10e (mixed system)[3]

1 References to 7215 IXS may be appended with (AA variant) or (AB variant) to indicate the chassis variant. Both variants are 7215 IXS platforms; they are identified by part numbers ending with AA or AB.

2 References to the 7250 IXR platform group may be appended with (including mixed systems) or (excluding mixed systems) to indicate support for a mix of 7250 IXR Gen 2c+ (IMM2) and 7250 IXR Gen 3 (IMM3) line cards in the same chassis.

3 References to this platform as part of 7250 IXR (mixed system) indicate mixed system support of 7250 IXR Gen 2c+ (IMM2) and 7250 IXR Gen 3 (IMM3). That is, the 7250 IXR-6e and 7250 IXR-10e can hold and support both IMM2 and IMM3 at the same time.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

2 What's new

There have been no updates in this document since it was last released.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

3 Show routines

This chapter provides a tutorial on how to create a routine, or set of instructions, that results in a custom show command. It also provides a detailed description of all the classes and utility functions used to create custom show commands.

Before creating a show routine, the following is recommended:

- Whenever you receive Data from the server, print it using:

  `print(str(data))`

  This makes it easier to visualize the data hierarchy.
- While building the SchemaNode and populating the Data structure, do not focus on the layout of your show routine. Instead, use the output of the following:

  `show <your-routine> | as json`

  This JSON output contains all the information currently in your show routine, in the correct hierarchy. After the JSON output looks correct, then plan how to format it.

Several show routines are available in `/opt/srlinux/python/virtual-env/lib/python3.11/dist-packages/srlinux/mgmt/cli/plugins/reports` that you can use as examples.

3.1 Creating a show routine

To create a show routine, you perform the following high-level steps:

1. Build a SchemaNode to describe the data's data model the show routine will construct.
   Procedure: Building the SchemaNode
2. Retrieve the state from the management server using **state.server_data_store.get_data(<path>)**
   Procedure: Retrieving the state from the management server
3. Populate a Data object with all the data (keys/fields/…) of the show routine.
   Procedure: Populating a data object
4. Add Formatter instances to determine how the data is formatted.
   Procedure: Adding formatter instances
5. Implement the callback method to pass the Data structure to the **output.print_data** command.
   Procedure: Implementing the callback method
6. Use streaming to optimize reports when working with large amounts of data.
   Procedure: Using streaming to optimize reports

Example

After completing all steps, the following is an example of the output. As you perform each step in this section, you will see how this example is built.

```
--{ running }--[  ]--
```


© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

```
# show my-report *
=====================================
name       : interface-1
description: The first interface
admin-state: enable
-------------------------------------
Child-Id  Is-Cool
=================
24         no
42         yes
=====================================
name       : interface-2
description: The second interface
admin-state: disable
-------------------------------------
Child-Id  Is-Cool
=================
1337       yes
=====================================
```

3.1.1 Building the SchemaNode

About this task

Schema nodes describe a data model. Similar to the output of the tree command or the content of a YANG file, they indicate what lists, containers, keys, fields, and leaf-lists can be created.

Procedure

Step 1. To build a SchemaNode, start with a **FixedSchemaRoot()**

Then add your top-level list/container using **FixedSchemaNode.add_child()** as shown in the SchemaNode reference.

Example

```
from srlinux.schema import FixedSchemaRoot

def _get_my_schema(self):
    root = FixedSchemaRoot()
    interface = root.add_child(
        'interface',
        key='name',
        fields=['description', 'admin-state']
    )
    child = interface.add_child(
        'child',
        key='Child-Id',
        fields=['Is-Cool']
    )
```

The code above generates a data model for the following YANG model.

```
list interface {
    key "name";
    leaf "description";
    leaf "admin-state";
    list child {
        key "Child-Id";
        leaf "Is-Cool";
```


© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

```
    }
}
```

Step 2. Ensure that the filter auto-completes all fields by passing the schema node into the **add_command** call when you install the plug-in. This ensures that the filter operator (|) can auto-complete all fields.

Example

```
class Plugin(CliPlugin):
    '''
Adds a fancy show report named "my-report".
'''

    def load(self, cli, **_kwargs):
        cli.show_mode.add_command(
            Syntax('my-report').add_unnamed_argument('name'),
            update_location=False,
            callback=self._print,
            schema=self._get_my_schema(),
        )
```

3.1.2 Retrieving the state from the management server

Procedure

To retrieve the state, use **build_path()** to populate a path of the key you need to retrieve, and call **get_data**.

This returns a Data object pointing to the root of the data returned by the management server.

Example

```
from srlinux.location import build_path

def _fetch_state(self, state, arguments):
    path = build_path('/interface[name={name}]/
subinterface[index=*]', name=arguments.get('name'))

    return state.server_data_store.get_data(path, recursive=True)
```

3.1.3 Populating a data object

Procedure

With the data from the management server and a data model, populate the Data object.

Example

```
from srlinux.data import Data
from srlinux import strings

def _populate_data(self, server_data):
    result = Data(self._get_my_schema())

    for interface in server_data.interface.items():
```


© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

```
        data = result.interface.create(interface.name)
        data.description = interface.description
        data.admin_state = interface.admin_state

        self._add_children(data, interface.subinterface)

    return result

def _add_children(self, data, server_data):
    # server_data is an instance of DataChildrenOfType

    for subinterface in server_data.items():
        child = data.child.create(subinterface.index)

        cool_ids = [42, 1337]
        is_cool = subinterface.index in cool_ids
        child.is_cool = strings.bool_to_yes_no(is_cool)
```

3.1.4 Adding formatter instances

Procedure

To format the output, assign **Formatter** instances to the different Data objects. The type of Formatter determines whether the output is formatted using key value pairs, a grid-based table, or a custom format.

A list of all the built-in formatters is in the Formatters section.

Example

```
from srlinux.data import Border, ColumnFormatter, Data, TagValueFormatter, Borders, Indent

def _set_formatters(self, data):
    data.set_formatter(
        '/interface',
        Border(TagValueFormatter(), Border.Above | Border.Below | Border.Between,
        '='))

    data.set_formatter(
        '/interface/child',
        Indent(ColumnFormatter(ancestor_keys=False, borders=Borders.Header), indentation=
2))
```

3.1.5 Implementing the callback method

Procedure

The following shows how to implement the callback method that is used to complete the routine.

Example

```
def _print(self, state, arguments, output, **_kwargs):
    server_data = self._fetch_state(state, arguments)
    result = self._populate_data(server_data)
    self._set_formatters(result)
    output.print_data(result)
```


© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

3.1.6 Show routine code example

After you complete Steps 1 - 5, the show routine first shown in section Creating a show routine is now complete.

The following is an example of the complete show routine code.

```
from srlinux import strings
from srlinux.data import Border, ColumnFormatter, TagValueFormatter, Borders, Data, Indent
from srlinux.location import build_path
from srlinux.mgmt.cli import CliPlugin
from srlinux.schema import FixedSchemaRoot
from srlinux.syntax import Syntax

class Plugin(CliPlugin):
    def load(self, cli, **_kwargs):
        cli.show_mode.add_command(
            Syntax('my-report').add_unnamed_argument('name'),
            update_location=False,
            callback=self._print,
            schema=self._get_my_schema(),
        )

    def _print(self, state, arguments, output, **_kwargs):
        server_data = self._fetch_state(state, arguments)
        result = self._populate_data(server_data)
        self._set_formatters(result)
        output.print_data(result)

    def _get_my_schema(self):
        root = FixedSchemaRoot()
        interface = root.add_child(
            'interface',
            key='name',
            fields=['description', 'admin-state']
        )
        child = interface.add_child(
            'child',
            key='Child-Id',
            fields=['Is-Cool']
        )
        return root

    def _fetch_state(self, state, arguments):
        path = build_path('/interface[name={name}]/
subinterface[index=*]', name=arguments.get('name'))

        return state.server_data_store.get_data(path, recursive=True)
    def _populate_data(self, server_data):
        result = Data(self._get_my_schema())

        for interface in server_data.interface.items():
            data = result.interface.create(interface.name)
            data.description = interface.description
            data.admin_state = interface.admin_state

            self._add_children(data, interface.subinterface)

        return result

    def _add_children(self, data, server_data):
        # server_data is an instance of DataChildrenOfType
```


© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

```
        for subinterface in server_data.items():
            child = data.child.create(subinterface.index)

            cool_ids = [42, 1337]
            is_cool = subinterface.index in cool_ids
            child.is_cool = strings.bool_to_yes_no(is_cool)

    def _set_formatters(self, data):
        data.set_formatter(
            '/interface',
            Border(TagValueFormatter(), Border.Above | Border.Below | Border.Between, '='))
        data.set_formatter(
            '/interface/child',
            Indent(ColumnFormatter(ancestor_keys=False, borders=Borders.Header), indentation=
2))
```

3.1.7 Using streaming to optimize reports

About this task

The previous steps detail how to obtain data, and then separately print a report. With streaming, data is retrieved and begins printing immediately. This is useful for reports that have large amounts of data (for example, route tables) because printing begins immediately instead of waiting for the entire data collection to complete.

Perform the following to implement streaming.

Procedure

Step 1. Enter state.server_data_store.stream_data(<path>) instead of state.server_data_store.get_data(<path>) to retrieve server data.

Example

```
def _fetch_state(self, state, arguments):
    path = build_path('/interface[name={name}]/subinterface[index=*]',
    name=arguments.get('name'))
    return state.server_data_store.stream_data(path, recursive=True)
```

Step 2. When constructing data, flush the data using flush_fields() and flush_children(). If no data is flushed, it displays as though streaming was not implemented. Implement flushing as soon as you know that a node is finished (but not sooner).

Example

```
        data.synchronizer.flush_fields(data)

        for interface in server_data.interface.items():
            data = data_root.interface.create(interface.name)
            data.description = interface.description
            data.admin_state = interface.admin_state
            data.synchronizer.flush_fields(data)
            data_root.synchronizer.flush_children(data_root.interface)
```

Note: You cannot change fields after a flush_fields() is called, and you cannot create new child nodes for the list you called flush_children().

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Step 3. Enter output.stream_data instead of output.print_data. Because this is a context manager python class, it can be used as `with output.stream_data(result):`. When the `with` block exits, flush_fields() and flush_children() are called on every node to ensure everything prints at the end.

Example

```
def _print(self, state, arguments, output, **_kwargs):
    result = Data(arguments.schema)
    self._set_formatters(result)
    with output.stream_data(result):
        self._populate_data_V4(result)
```

Step 4. Ensure formatted output is aligned. If needed, the column width can be explicitly passed to the formatter.

Example

```
Pass width of columns to formatter ::
    ColumnFormatter(widths=[Percentage(10), 6, 10, Width(min_width=8,
    percent=20)])
```

Expected outcome

The following is an example of the complete show routine code using streaming.

```
from srlinux import strings
from srlinux.data import Border, ColumnFormatter, TagValueFormatter, Borders, Data, Indent
from srlinux.location import build_path
from srlinux.mgmt.cli import CliPlugin
from srlinux.schema import FixedSchemaRoot
from srlinux.syntax import Syntax

class Plugin(CliPlugin):
    def load(self, cli, **_kwargs):
        cli.show_mode.add_command(
            Syntax('my-report').add_unnamed_argument('name'),
            update_location=False,
            callback=self._print,
            schema=self._get_my_schema(),
        )

    def _print(self, state, arguments, output, **_kwargs):
        result = Data(arguments.schema)
        self._set_formatters(result)
        with output.stream_data(result):
            self._populate_data(result, state, arguments)

    def _get_my_schema(self):
        root = FixedSchemaRoot()
        interface = root.add_child(
            'interface',
            key='name',
            fields=['description', 'admin-state']
        )
        return root

    def _fetch_state(self, state, arguments):
        path = build_path('/interface[name={name}]/
        subinterface[index=*]', name=arguments.get('name'))
        return state.server_data_store.stream_data(path, recursive=True)

    def _populate_data(self, data_root, state, arguments):
```


© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

```
        server_data = self._fetch_state(state, arguments)
        data_root.synchronizer.flush_fields(data_root)
        for interface in server_data.interface.items():
            data = data_root.interface.create(interface.name)
            data.description = interface.description
            data.admin_state = interface.admin_state
            data.synchronizer.flush_fields(data)


    def _set_formatters(self, data):
        data.set_formatter(
            '/interface',
            Border(TagValueFormatter(), Border.Above | Border.Below | Border.Between, '='))
```


© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

4 Managing CLI plug-ins

This chapter contains procedures for installing, modifying, and removing a CLI plug-in on the SR Linux device.

4.1 Installing a CLI plug-in

About this task

To install a CLI plug-in, perform the following:

Procedure

Step 1. Open an SSH session.

Step 2. Place the completed plug-in file into one of the following directories:

- `/etc/opt/srlinux/cli/plugins`
- `$HOME/cli/plugins`

The `/etc/opt/srlinux/cli/plugins` directory is the global plug-ins directory.

With the `$HOME/cli/plugins` directory, $HOME is resolved to the users home directory. For example: `/home/<user_name>/cli/plugins`.

Plug-ins are read from the global directory first (`/etc/opt/srlinux/cli/plugins`), then the per-user home directory with the user directory overriding any previously defined global plug-ins.

Step 3. To test the new plug-in, restart the SR Linux CLI by closing the current SSH session and reconnecting using SSH.

4.2 Modifying a CLI plug-in

About this task

To modify an existing CLI plug-in, perform the following:

Procedure

Step 1. Open an SSH session.

Step 2. Modify the CLI plug-in and place the updated file into one of the following directories:

- `/etc/opt/srlinux/cli/plugins`
- `$HOME/cli/plugins`

Step 3. Restart the SR Linux CLI by closing the current SSH session and reconnecting using SSH.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

4.3 Removing a CLI plug-in

About this task

To remove an existing plug-in from the SR Linux CLI, perform the following:

Procedure

Step 1. Open an SSH session.

Step 2. Delete the CLI plug-in file from its current directory (one of the following):

- `/etc/opt/srlinux/cli/plugins`
- `$HOME/cli/plugins`

Step 3. Restart the SR Linux CLI by closing the current SSH session and reconnecting using SSH.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

5 Classes and utility functions

This chapter provides descriptions of the classes and utility functions used to write custom show commands.

5.1 Formatters

A number of built-in formatters are available or you can create your own using the Format utilities :

ColumnFormatter:

Formats the data using a column-based table, which supports a number of ways to customize the look-and-feel.

Example: ColumnFormatter

```
+----------+----------+--------------+
| entry-id |  source  | destination  |
+==========+==========+==============+
| 10       | 10.0.0.1 | 10.0.0.8     |
+----------+----------+--------------+
```

TagValueFormatter:

Formats the data using a single **tag: value** pair on each line.

Example: TagValueFormatter

```
entry-id    : 10
source      : 10.0.0.1
destination : 10.0.0.8
```

TagValueWithKeyLineFormatter:

Formats the data using:

- a single line to print the name and keys
- a line for each field and leaf-list, formatted as a "tag: value" pair

Example: TagValueWithKeylineFormatters

```
Entry 10
source      : 10.0.0.1
destination : 10.0.0.8
```

Built-in decorators are also available to wrap around a formatter to add embellishments to the output. The following table lists the built-in decorators.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Table 2: Built-in decorators

Built-in decorator	Description
Indent	Adds an indentation before every output line.
Border	Adds lines above, below, or between the printed entries.
Header	Adds a header above the first printed entry.
Footer	Adds a footer below the last printed entry.
Whiteline	Adds an empty line above, below, or between the printed entries.
FilteredFormatter	Filters out fields/leaf-lists.

5.1.1 ColumnFormatter

Class **srlinux.data.ColumnFormatter**(ancestor_keys=True, horizontal_alignment=None, vertical_alignment=None, borders=None

Formats the specific Data object as a column-based table.

Example: Column-based table

```
+----------+------------------+--------------------+---------------+
| Entry id |     Ip prefix    |  Origin protocol   |   Next hop    |
+==========+==================+====================+===============+
| 1        | 192.0.2.0/24     | local_aggregate    | None          |
| 2        | 198.168.0.0/16   | directly_connected | None          |
+----------+------------------+--------------------+---------------+
```

The output can be customized using the following constructor arguments:

ancestor_keys : bool or list

The **bool** construct controls whether the ancestor keys are added as columns to the output table:

- True - (the default) includes all ancestor keys
- False - does not include any ancestor keys

A list provides more granular control. The list must contain a value for each ancestor key, and can contain:

- None - suppresses the key
- A string to specify the column key to use for the ancestor key

Example: List with none value

When passed [None, "A", None], the first and third ancestor key are dropped, and the second is renamed to "A".

horizontal_alignment : dict{str: Alignment}

Dictionary mapping column-names to their horizontal alignment (Alignment.Left/Center/Right). Columns not mentioned are left-aligned.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

vertical_alignment : dict{str: Alignment}

Dictionary mapping column-names to their vertical alignment (Alignment.Top/Middle/Bottom). Columns not mentioned are top-aligned.

borders : Borders

Combination of Borders values indicating which borders to print. Defaults to "Borders.Outside | Borders.Header | Borders.Columns".

Class **srlinux.data.Alignment**

The values used to align data in the table cells. The following table lists the alignment values.

Table 3: Cell alignment values

Alignment value	Description
Left= 1	Horizontally aligns the data to the left
Right= 2	Horizontally aligns the data to the right
Center= 3	Horizontally centers the data
Top= 4	Vertically aligns the data to the top
Middle= 5	Vertically centers the data
Bottom= 6	Vertically aligns the data to the bottom

Class **srlinux.data.Borders**

Specifies border type when drawing a table. Values can be combined together using the symbol '|'. For example: **Borders.Outside | Borders.Header** draws a border around the table and a line below the header. The following table defines the border values to use when drawing a table.

Table 4: Types of table borders

Table border	Description
Nothing= 0	Draws no borders
Outside= 1	Draws a border around the table
Header= 2	Draws a horizontal line between the header and the first row
Rows= 4	Draws a horizontal line between the rows
Columns= 8	Draws a vertical line between the columns

5.1.2 TagValueFormatter

Class **srlinux.data.TagValueFormatter**(*filter=None*)

Formats the specified Data object as a list of "tag: value" pairs (one on each line).

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Example

```
key  : <name>
field: <value>
```

5.1.3 TagValueWithKeyLineFormatter

Class **srlinux.data.TagValueWithKeyLineFormatter**(*filter=None*)

Formats the specified Data object as a single line with the name and the keys, followed by a list of "tag: value" pairs (one on each line).

Example

```
node <name> id <id>
field: <value>
```

5.1.4 Indent

Class **srlinux.data.Indent**(*formatter, indentation=' '*)

Decorator that indents every line printed by the wrapped formatter.

Example

```
Indent(MyOtherFormatter(), 6)
Indent(MyOtherFormatter(), '      ')
```

Either of the examples shown above adds six spaces before every line printed by *MyOtherFormatter*. The following table defines the indent arguments.

Table 5: Indent arguments

Argument	Description
indentation: str or int	The indent string put before every line, or an integer that indicates the amount of spaces to add.

5.1.5 Border

Class **srlinux.data.Border**(*formatter, position=None, character='-'*)

Decorator that prints a border line above, below, or above and below another formatter.

Example

```
Border(MyOtherFormatter(), Border.Above | Border.Below, '+')
```

This example prints a border line of ++++++++++ above and below the output of the other formatter. The following table lists the border line arguments.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Table 6: Border line arguments

Argument	Description
position : Border	Controls where the border lines are drawn. Multiple values can be combined together using the "|" symbol.
Border.Above	Prints a line above the first Data entry. Defaults to printing a line above and below.
Border.Below	Prints a line below the last Data entry. Defaults to printing a line above and below.
Border.Between	Prints a line between each Data entry. Defaults to printing a line above and below.
character: char (optional)	Defines the character used to draw the border line. Defaults to "-".

5.1.6 Header

Class **srlinux.data.Header**(*formatter, text, character='-'*)

Decorator that prints a header above another formatter.

Example

```
Header(
    MyOtherFormatter(),
    text='The header text',
    character='+'
)
```

This example prints:

```
++++++++++++++++++++++++
The header text
++++++++++++++++++++++++
<snip here is the output of MyOtherFormatter>
```

The following table defines the header arguments.

Table 7: Header arguments

Argument	Description
text: str	Defines the header text, which can contain new lines.
character: char (optional)	Defines the character used to draw the border. Defaults to "-".

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

5.1.7 Footer

Class **srlinux.data.Footer**(*formatter, text, character='-'*)

Decorator that prints a footer below another formatter.

Example

```
Footer(
    MyOtherFormatter(),
    text='The footer text',
    character='+'
)
```

This example prints:

```
<snip here is the output of MyOtherFormatter>
++++++++++++++++++++++++
The footer text
++++++++++++++++++++++++
```

The following table defines the footer arguments.

Table 8: Footer arguments

Argument	Description
text: str	Defines the footer text, which can contain new lines.
character: char	Defines the character used to draw the border. Defaults to "-".

5.1.8 Whiteline

*i*Class **srlinux.data.Whiteline**(*formatter, position=None*)

Decorator that prints an empty line above, below, and between entries of another formatter.

Example

```
Whiteline(MyOtherFormatter(), Whiteline.Above | Whiteline.Below)
```

This example prints an empty line above and below the output of the other formatter.

The following table defines the Whiteline arguments.

Table 9: Whiteline arguments

Argument	Description
position : Whiteline	Controls where the empty lines are drawn. Multiple values can be combined together using "|".

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Argument	Description
Whiteline.Above	Prints a line above the first Data entry. Defaults to printing a line above and below.
Whiteline.Below	Prints a line below the last Data entry. Defaults to printing a line above and below.
Whiteline.Between	Prints a line between each Data entry. Defaults to printing a line above and below.

5.1.9 FilteredFormatter

*i*Class **srlinux.data.FilteredFormatter**(*formatter, schema, fields=[], leaflists=[]*)

Decorator that only displays the selected fields and leaf-lists.

Example: FilteredFormatter

```
FilteredFormatter(
    MyOtherFormatter(),
    schema=data.schema,
    fields=['field-to-keep', 'other-field-to-keep'],
    leaflists=['leaflist-to-keep', 'other-leaflist-to-keep'],
)
```

A common use case for this decorator is to enhance the format of some fields, but keeps the original field values available for when the output is formatted as JSON.

For the next example, both the original fields and the combined field are added to the Data object, and the original fields are filtered out for formatting.

Example: Both fields added to data object

```
data = Data(schema)

# The 2 original fields. Added to data so that 'show <snip> | as json' displays them
in a useful fashion.
data.source = '1.2.3.4'
data.destination = '5.6.7.8'

# The combined field we want to show in the show report.
data.flow = f'{data.source} -> {data.destination}'

# Only show the combined field in the show report.
data.formatter = FilteredFormatter(
    TagValueFormatter(),
    schema=data.schema,
    fields=['flow']
)
```

The following table defines the available FilteredFormatter arguments.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Table 10: FilteredFormatter arguments

Argument	Description
schema : SchemaNode	Defines the schema of the Data object this formatter is applied to
fields : list of str	Defines the names of the fields to display. Any field not mentioned is omitted from the output. The default is to remove all fields.
leaflists : list of str	Defines the names of the leaf-lists to display. Any leaf-list not mentioned is omitted from the output. The default is to remove all leaf-lists.

5.2 Format utilities

If the built-in formatters are not sufficient, you can add a summary line or other modifications. The following utilities can be used when writing your own Formatter.

5.2.1 ColumnPrinter

*i*Class **srlinux.data.ColumnPrinter**(*columns, max_width, horizontal_alignment, vertical_alignment, borders, filter=None*)

Utility class to print a set of rows as a column-based table.

Example

```
+----------+-------------------+
| Entry id |     Ip prefix     |
+==========+===================+
| 1        | 198.51.100.0/24   |
| 2        | 203.0.113.0/32    |
+----------+-------------------+
```

This output is generated with the following:

```
printer = ColumnPrinter(['Entry id', 'Ip prefix'], borders=Borders.Outside, max_widt
h=80)

printer.add_row([1, '198.51.100.0/24'])
printer.add_row([2, '203.0.113.0/32'])

printer.iter_format()
# Returns
# (
#    '+----------+-------------------+',
#    '| Entry id |     Ip prefix     |',
#    '+==========+===================+',
#    '| 1        | 198.51.100.0/24   |',
#    '| 2        | 203.0.113.0/32    |',
#    '+----------+-------------------+'
```


© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

```
# )
```

The following table defines the constructor arguments that can be used to customize the output.

Table 11: ColumnPrinter constructor arguments

Constructor argument	Description
horizontal_alignment : dict{str: Alignment}	Dictionary mapping of column-names to their horizontal alignment (Alignment.Left/ Center/Right). Columns not mentioned here are left-aligned.
vertical_alignment : dict{str: Alignment}	Dictionary mapping of column-names to their vertical alignment (Alignment.Top/ Middle/Bottom). Columns not mentioned here are top-aligned.
borders : Borders	Combining borders values that indicate what borders can be drawn. Defaults to "Borders.Outside | Borders.Header | Borders.Columns".
filter : Filter	Filters out fields from the output. Fields that do not match the filter are not printed.

5.2.2 TagValuePrinter

*i*Class **srlinux.data.TagValuePrinter**(*tags, max_width, filter=None*)

Utility class to print a set of "tag: value" pairs.

Example

```
printer = TagValuePrinter(['first', 'second'], max_width=80)
printer.iter_format(['value', 'other-value'])
# Returns (
#    'first : value',
#    'second: other-value',
# )
```

If None (or '' or []) is passed in as a value, the item is skipped in the output:

```
printer.iter_format([None, 'other-value'])
# Returns (
#    'second: other-value',
# )
```

The following table defines the TagValuePrinter arguments.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Table 12: TagValuePrinter arguments

Argument	Description
filter : Filter	Filters out fields/leaf-lists from the output. Fields that do not match the filter are not printed.

5.2.3 TagValueWithKeyLinePrinter

*i*Class **srlinux.data.TagValueWithKeyLinePrinter**(*name, keys, tags, max_width, filter=None*)

Utility class to print a single line with the name and the keys, followed by a list of "tag: value" pairs (one on each line).

Example

```
node <name> id <id>
field: <value>
```

The following is an example of this usage:

```
printer = TagValueWithKeyLinePrinter(name='node', keys=['key'], tags=['first-
field', 'second-field'], max_width=80)
printer.iter_format(keys=[<name>], values=['value', 'other-value'])
# Returns (
#    'node <name>',
#    '  first-field : value',
#    '  second-field: other-value',
# )
```

If None (or '' or []) is passed in as a value, the item is skipped in the output:

```
printer.iter_format(keys=['<name>'], [None, 'other-value'])
# Returns (
#    'node <name>',
#    '  second-field: other-value',
# )
```

The following table defines theTagValueWithKeyLinePrinter arguments.

Table 13: TagValueWithKeyLinePrinter arguments

Argument	Description
filter : Filter	Filters out fields/leaf-lists from the output. Fields that do not match the filter are not printed.

5.2.4 print_line

srlinux.data.print_line(*width, character='-'*)

Returns a line of length "width", consisting of the specified character.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

5.2.5 print_double_line

srlinux.data.print_double_line(*width*)

Returns a line of length "width" consisting of ==========.

5.2.6 indent

srlinux.data.indent(*values, indentation*)

Indents each value with the specified indentation. The indentation can either be a string, or an integer indicating the number of spaces to use for the indentation.

5.2.7 format_value

srlinux.data.format_value(*value*)

Formats the Data value as a string, which works for key, field, and leaf-list values of all accepted types (number, string, bool), even if the field/leaf-list is absent.

5.3 Data

The class used to represent all data; both the data retrieved from the server and the data displayed in the show report.

Class **srlinux.data.data.Data**(*schema, parent=None, **keys*)

Allows easy access to a configuration/state instance. When creating a top-level Data object, you must specify an instance of a **SchemaNode**. The code analyzes the schema, and makes all fields, keys, leaf-lists, and children accessible as attributes.

Example: SchemaNode

Assume that this is the data model:

```
list interface {
    key 'name';
    field 'admin-state';
    leaflist 'values';
    list subinterface {
        key 'id';
    }
}
```

You can then:

- Get the keys:

  ```
  value = data.name
  ```

- Get and set the fields:

  ```
  value = data.admin_state # returns the value or None if unset
  ```


© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

```
data.admin_state = 'enabled'
```

- Get and set leaflists:

```
value = data.values # returns a list
data.values = ['a', 'b']
```

- Access children:

```
child = data.subinterface.create(42) # Creates the subinterface with id '42'
child = data.subinterface.get(42)
if data.subinterface.exists(42):
    # Returns True/False
for si in data.subinterface.items():
    # Walks all subinterfaces, ordered by their key
```



Note: Names are changed so that any character that is not a to z, A to Z, or 0 to 9 is replaced by an "_".

Children

When accessing a child (data.subinterface in the preceding example), an instance of DataChildrenOfType is returned. Follow the link to see all the accessors it provides.

Values

All key/field/leaf-list values are of the following types:

- bool
- integer
- string

Formatters

To generate the show report, **Formatter** objects are used. These can be tied to a specific Data object using two methods:

- By assigning a formatter to the **Data.formatter** property.
- By using **Data.set_formatter()**.

Both methods assign the formatter to all sibling Data objects. Calling the following sets the formatter for all interfaces and not just for subinterface 42.

Example: Formatters

```
data.subinterface.get(42).formatter = ColumnFormatter()
```

The following table lists the different types of formatters.

Table 14: Types of formatters

Formatter	Description
parent	Returns the parent Data object, or None if this is the root.
schema	Returns the **SchemaNode**.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Formatter	Description
key_names	Returns an iterator over the names of the keys.
key_values	Returns an iterator over the key values. Iterators are returned in the order specified by *self.key_names*, which is the same as the order that the keys were added to the **SchemaNode**.
get_key(*name*)	Returns the value of the key with the specified name.
keys_dict	Returns a "name: value" dictionary of the keys.
type_name	Returns the type-name, which is *self.schema.name*.
field_names	Returns an iterator over the names of the fields.
field_values	Returns an iterator over the field values. Iterators are returned in the order specified by *self.field_names*, which is the same as the order that the fields were added to the **SchemaNode**.
set_field*(name, value*)	Assigns the value to the field with the specified name.
get_field(*name, default=None*)	Returns the value of the field with the specified name, or the default if the field is unset.
is_field_set(*name*)	Returns True if the field is set.
leaflist_names	Returns an iterator over the names of the leaf-lists.
leaflist_values	Returns an iterator over the leaf-list values. Iterators are returned in the order specified by *self.leaflist_names*, which is the same as the order that the leaf-lists were added to the **SchemaNode**.
get_leaflist(*name*)	Returns a list containing the values of the leaf-list with the specified name. This list is empty if the leaf-list is unset.
set_leaflist(*name, value*)	Assigns the value to the leaf-list with the specified name. The value must be a list.
is_leaflist_set(*name*)	Returns True if the leaf-list is set.
child_names	Returns an iterator over the names of the children.
get_children(*name*)	Returns the DataChildrenOfType instance that contains all the children of the specified type. This returned object is mutable and can be used to walk/retrieve/add children.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Formatter	Description
iter_children_by_type(*predicate=<function Data.<lambda>>*)	Iterates over all DataChildrenOfType instances for which the predicate is True. By default, this returns all children.
iter_children()	Iterates over all child instances.
get(*name*)	Returns the value of the specified key, field, leaf-list, or child.
get_annotations(*name=None*)	Returns a list containing the annotations of this node (if called with no arguments) or the field with the specified name.
add_annotation(*annotation, name=None*)	Adds the specified annotation to this node (when called with a single argument) or to the field with the specified name (when called with two arguments). The annotation must be an instance of **Annotation**.
formatter	Returns the **Formatter** that can be used to generate the show report for this Data object.
iter_format(*max_width*)	Invokes the **Formatter** of this Data object. Returns an iterator over the formatted output lines.
iter_format_children(*max_width*)	Invokes the **Formatter** of all children of this Data object. Returns an iterator over the formatted output lines.
set_formatter(*schema, formatter*)	Adds a **Formatter** to the Data object with the specified schema. The schema can be specified as an XPath string (without keys). For example, "/interface/subinterface".
get_schema(*path*)	Get the **SchemaNode** of the Data object with the specified path. The path must be an XPath string, for example, "/interface/subinterface".

5.4 DataChildrenOfType

Use this class when you need to access children through a Data object. It allows you to retrieve, create, and iterate all children.

Class **srlinux.data.data.DataChildrenOfType**(*schema, parent*)

The children of a Data object of a single type.

Returned by **Data.get_children()** or by accessing the attribute with the child name (for example, Data.interface). Most methods require you to pass a value for each key defined in the schema.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Example: No keys

If the schema has no keys, use:

```
data.node.get()
data.node.create()
data.node.exists()
```

Example: Single key

If the schema has a single key, this becomes:

```
#node has a single key 'name'

data.node.get('abc')
data.node.create('abc')
data.node.exists('abc')

# or

data.node.get(name='abc')
data.node.create(name='abc')
data.node.exists(name='abc')
```

Example: Multiple keys

If the schema has a multiple keys, specify them all in the correct order:

```
# node has 2 keys, 'name' and 'id'

data.node.get('abc', 1)
data.node.create('abc', 1)
data.node.exists('abc', 1)

# or

data.node.get(name='abc', id=1)
data.node.create(name='abc', id=1)
data.node.exists(name='abc', id=1)
```

The following table defines the **DataOfChildrenType** Attributes.

Table 15: DataOfChildrenType attributes

Attribute	Description
get(**args, **kwargs*)	Returns an existing child with the specified keys. Generates an AttributeError if a wrong number of keys is specified, and KeyError if there is the child does not exist.
exists(**args, **kwargs*)	Returns True if a child with the specified keys exists. Generates an AttributeError if a wrong number of keys is given.
create(**args, **kwargs*)	Creates and returns a child with the specified keys. If this child already exists, the existing child is returned

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Attribute	Description
	(and no changes are made). Generates an Attribute Error if a wrong number of keys is given.
count()	Counts the number of children.
is_empty	Returns True if there are no children of this type.
items()	Iterates over all children of this type and are sorted based on their keys.
clear()	Removes all children of this type.
formatter	Returns the **Formatter** that can be used to generate the show report for the Data object.
iter_format(*max_width*)	Invokes the **Formatter.iter_format_type()** of these Data objects. Returns an iterator over the formatted output lines.

5.5 SchemaNode

srlinux.schema.fixed_schema.FixedSchemaNode.add_child(*self, child_name, key=None, keys=[], field=None, fields=[], leaflist=None, leaflists=[], importance=<ShowImportance.High: 3>*)

Adds a list/container to the current node, which allows you to specify the keys, fields, and leaf-lists of the new child.


The following table defines the SchemaNode arguments.

Table 16: Schema Node arguments

Argument	Description
child_name : str	The name specified for the newly created child.
key : str or None	If not None, a key with the specified name is added.
keys : list of str	The names of the keys to be added.
field : str or None	If not None, a field with the specified name is added.
fields : list of str	The names of the fields that are added.
leaflist : str or None	If not None, a leaf-list with the specified name is added.
leaflists : list of str	The names of the leaf-lists to be added.

© 2026 Nokia.
Use subject to Terms available at: www.nokia.com/terms.

Customer document and product support



Customer documentation

Customer documentation welcome page



Technical support

Product support portal



Documentation feedback

Customer documentation feedback